

# SERVICE MANUAL

N750WU / N751WU

*notebook*





**Notebook Computer**  
**N750WU / N751WU**  
**Service Manual**

## Notice

The company reserves the right to revise this publication or to change its contents without notice. Information contained herein is for reference only and does not constitute a commitment on the part of the manufacturer or any subsequent vendor. They assume no responsibility or liability for any errors or inaccuracies that may appear in this publication nor are they in anyway responsible for any loss or damage resulting from the use (or misuse) of this publication.

This publication and any accompanying software may not, in whole or in part, be reproduced, translated, transmitted or reduced to any machine readable form without prior consent from the vendor, manufacturer or creators of this publication, except for copies kept by the user for backup purposes.

Brand and product names mentioned in this publication may or may not be copyrights and/or registered trademarks of their respective companies. They are mentioned for identification purposes only and are not intended as an endorsement of that product or its manufacturer.

Version 1.0  
September 2017

## Trademarks

**Pentium and Celeron** are trademarks of Intel Corporation.

**Windows®** is a registered trademark of Microsoft Corporation.

Other brand and product names are trademarks and /or registered trademarks of their respective companies.



## About this Manual

This manual is intended for service personnel who have completed sufficient training to undertake the maintenance and inspection of personal computers.

It is organized to allow you to look up basic information for servicing and/or upgrading components of the *N750WU* / *N751WU* series notebook PC.

The following information is included:

Chapter 1, Introduction, provides general information about the location of system elements and their specifications.  
Chapter 2, Disassembly, provides step-by-step instructions for disassembling parts and subsystems and how to upgrade elements of the system.

Appendix A, Part Lists

Appendix B, Schematic Diagrams

Appendix C, Updating the FLASH ROM BIOS

## Preface

---

### IMPORTANT SAFETY INSTRUCTIONS

Follow basic safety precautions, including those listed below, to reduce the risk of fire, electric shock and injury to persons when using any electrical equipment:

1. Do not use this product near water, for example near a bath tub, wash bowl, kitchen sink or laundry tub, in a wet basement or near a swimming pool.
2. Avoid using a telephone (other than a cordless type) during an electrical storm. There may be a remote risk of electrical shock from lightning.
3. Do not use the telephone to report a gas leak in the vicinity of the leak.
4. Use only the power cord and batteries indicated in this manual. Do not dispose of batteries in a fire. They may explode. Check with local codes for possible special disposal instructions.
5. This product is intended to be supplied by a Listed Power Unit with an AC Input of 100 - 240V, 50 - 60Hz, DC Output of 19V, 2.1A (**40 Watts**) minimum AC/DC Adapter.

### CAUTION

**This Computer's Optical Device is a Laser Class 1 Product**

### FCC Statement

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

This device may not cause harmful interference.

This device must accept any interference received, including interference that may cause undesired operation.


## Instructions for Care and Operation

The notebook computer is quite rugged, but it can be damaged. To prevent this, follow these suggestions:


1. **Don't drop it, or expose it to shock.** If the computer falls, the case and the components could be damaged.



2. **Keep it dry, and don't overheat it.** Keep the computer and power supply away from any kind of heating element. This is an electrical appliance. If water or any other liquid gets into it, the computer could be badly damaged.




3. **Follow the proper working procedures for the computer.** Shut the computer down properly and don't forget to save your work. Remember to periodically save your data as data may be lost if the battery is depleted.



## Preface


4. **Avoid interference.** Keep the computer away from high capacity transformers, electric motors, and other strong magnetic fields. These can hinder proper performance and damage your data.
5. **Take care when using peripheral devices.**



## Power Safety

The computer has specific power requirements:

- Only use a power adapter approved for use with this computer.
- Your AC adapter may be designed for international travel but it still requires a steady, uninterrupted power supply. If you are unsure of your local power specifications, consult your service representative or local power company.
- The power adapter may have either a 2-prong or a 3-prong grounded plug. The third prong is an important safety feature; do not defeat its purpose. If you do not have access to a compatible outlet, have a qualified electrician install one.
- When you want to unplug the power cord, be sure to disconnect it by the plug head, not by its wire.
- Make sure the socket and any extension cord(s) you use can support the total current load of all the connected devices.
- Before cleaning the computer, make sure it is disconnected from any external power supplies.



### Power Safety Warning

Before you undertake any upgrade procedures, make sure that you have turned off the power, and disconnected all peripherals and cables (including telephone lines and power cord). It is advisable to also remove your battery in order to prevent accidentally turning the machine on.

## Battery Precautions

- Only use batteries designed for this computer. The wrong battery type may explode, leak or damage the computer.
- Do not continue to use a battery that has been dropped, or that appears damaged (e.g. bent or twisted) in any way. Even if the computer continues to work with a damaged battery in place, it may cause circuit damage, which may possibly result in fire.
- Recharge the batteries using the notebook's system. Incorrect recharging may make the battery explode.
- Do not try to repair a battery pack. Refer any battery pack repair or replacement to your service representative or qualified service personnel.
- Keep children away from, and promptly dispose of a damaged battery. Always dispose of batteries carefully. Batteries may explode or leak if exposed to fire, or improperly handled or discarded.
- Keep the battery away from metal appliances.
- Affix tape to the battery contacts before disposing of the battery.
- Do not touch the battery contacts with your hands or metal objects.

## Battery Guidelines

The following can also apply to any backup batteries you may have.

- If you do not use the battery for an extended period, then remove the battery from the computer for storage.
- Before removing the battery for storage charge it to 60% - 70%.
- Check stored batteries at least every 3 months and charge them to 60% - 70%.




### Battery Disposal

The product that you have purchased contains a rechargeable battery. The battery is recyclable. At the end of its useful life, under various state and local laws, it may be illegal to dispose of this battery into the municipal waste stream. Check with your local solid waste officials for details in your area for recycling options or proper disposal.

### Caution

Danger of explosion if battery is incorrectly replaced. Replace only with the same or equivalent type recommended by the manufacturer. Discard used battery according to the manufacturer's instructions.

### Battery Level

Click the battery icon  in the taskbar to see the current battery level and charge status. A battery that drops below a level of 10% will not allow the computer to boot up. Make sure that any battery that drops below 10% is recharged within one week.

### Related Documents


You may also need to consult the following manual for additional information:

#### User's Manual on CD/DVD

This describes the notebook PC's features and the procedures for operating the computer and its ROM-based setup program. It also describes the installation and operation of the utility programs provided with the notebook PC.

### System Startup

1. Remove all packing materials.
2. Place the computer on a stable surface.
3. Insert the battery and make sure it is locked in position.
4. Securely attach any peripherals you want to use with the computer (e.g. keyboard and mouse) to their ports.
5. **When first setting up the computer use the following procedure** (as to safeguard the computer during shipping, the battery will be locked to not power the system until first connected to the AC/DC adapter and initially set up as below):
  - Attach the AC/DC adapter cord to the DC-In jack on the left of the computer, then plug the AC power cord into an outlet, and connect the AC power cord to the AC/DC adapter and **leave it there for 6 seconds or longer**.
  - Remove the adapter cord from the computer's DC-In jack, and then plug it back in again; the battery will now be unlocked.
6. Use one hand to raise the lid/LCD to a comfortable viewing angle (do not exceed 120 degrees); use the other hand (as illustrated in Figure 1) to support the base of the computer (**Note: Never** lift the computer by the lid/LCD).
7. Press the power button to turn the computer "on".



*Figure 1*  
**Opening the Lid/LCD/  
Computer with AC/DC  
Adapter Plugged-In**

#### Powering the Computer On

After every disassembly, make sure that the bottom case's screws are all inserted and tightened before turning the computer on.

#### Shut Down

Note that you should always shut your computer down by choosing **Shut Down** from the **Start** Menu.

This will help prevent hard disk or system problems.

# Contents

## Introduction .....1-1

Overview .....	1-1
Specifications .....	1-2
External Locator - Top View with LCD Panel Open .....	1-4
External Locator - Front & Right Side Views .....	1-5
External Locator - Left Side & Rear View .....	1-6
External Locator - Bottom View .....	1-7
Mainboard Overview - Top (Key Parts) .....	1-8
Mainboard Overview - Bottom (Key Parts) .....	1-9
Mainboard Overview - Top (Connectors) .....	1-10
Mainboard Overview - Bottom (Connectors) .....	1-11

## Disassembly .....2-1

Overview .....	2-1
Maintenance Tools .....	2-2
Connections .....	2-2
Maintenance Precautions .....	2-3
Disassembly Steps .....	2-4
Removing the Battery .....	2-5
Removing the Keyboard .....	2-6
Removing the Hard Disk Drive .....	2-7
Removing the 2nd Hard Disk from Caddy Bay .....	2-9
Removing the Optical (CD/DVD) Device .....	2-10
Removing the System Memory (RAM) .....	2-11
Removing the Wireless LAN Module .....	2-13
Wireless LAN, Combo, 3G & LTE Module Cables .....	2-14
Removing the 3G Module .....	2-15
Removing and Installing the M.2 SSD Module .....	2-16
Removing the CCD .....	2-18

## Part Lists .....A-1

Part List Illustration Location .....	A-2
Top .....	A-3
Bottom .....	A-4
LCD .....	A-5
HDD .....	A-6
HDD Caddy .....	A-7
DVD .....	A-8
MB .....	A-9

## Schematic Diagrams.....B-1

System Block Diagram .....	B-2
Processor 1/6 .....	B-3
Processor 2/6 .....	B-4
Processor 3/6 .....	B-5
Processor 4/6 .....	B-6
Processor 5/6 .....	B-7
Processor 6/6 .....	B-8
DDR4 CHA SO_DIMM_0 .....	B-9
DDR4 CHB SO_DIMM_0 .....	B-10
Panel, Inverter .....	B-11
VGA RTD2168 .....	B-12
Card Reader & LAN RTL8411B .....	B-13
HDMI, RJ45, Fan, TPM .....	B-14
PCH 1/9 .....	B-15
PCH 2/9 .....	B-16
PCH 3/9 .....	B-17
PCH 4/9 .....	B-18
PCH 5/9 .....	B-19
PCH 6/9 .....	B-20
PCH 7/9 .....	B-21
PCH 8/9 .....	B-22

## Preface

PCH 9/9 .....	B-23
M.2 (WLAN, 3G, SSD) .....	B-24
Audio Codec .....	B-25
PS8330B .....	B-26
AR_TBT .....	B-27
AR_Power .....	B-28
ASM1543 .....	B-29
TPS65982 .....	B-30
Type C .....	B-31
USB .....	B-32
HDD, ODD, LED .....	B-33
CCD, MIC, LID, I/O Connector .....	B-34
KBC ITE IT8587 .....	B-35
5V, 5VS, 3.3V, 3.3VS, 3.3VA .....	B-36
VDD3, VDD5 .....	B-37
DDR 1.2V/0.62VS, 2.5V .....	B-38
VCC_CORE, VCCGT .....	B-39
VCORE, VCCGT Output Stage .....	B-40
VCCSA .....	B-41
VCCIO .....	B-42
1.0DX_VCCSTG/VCCSFR_OC, 3.3VA .....	B-43
Charger, AC-In .....	B-44
Audio Board .....	B-45
Click Board .....	B-46
LID SW Board .....	B-47
Caddy Bay Board .....	B-48
Power Seq. ....	B-49

## Updating the FLASH ROM BIOS..... C-1

Download the BIOS .....	C-1
Unzip the downloaded files to a bootable CD/DVD/ or USB Flash drive .....	C-1

Set the computer to boot from the external drive .....	C-1
Use the flash tools to update the BIOS .....	C-2
Restart the computer (booting from the HDD) .....	C-2




# Chapter 1: Introduction

## Overview

This manual covers the information you need to service or upgrade the *N750WU / N751WU* series notebook computer. Information about operating the computer (e.g. getting started, and the *Setup* utility) is in the *User's Manual*. Information about drivers (e.g. VGA & audio) is also found in the *User's Manual*. The manual is shipped with the computer.

Operating systems (e.g. *Window 10*, etc.) have their own manuals as do application softwares (e.g. word processing and database programs). If you have questions about those programs, you should consult those manuals.

The *N750WU / N751WU* series notebook is designed to be upgradeable. See [Disassembly on page 2 - 1](#) for a detailed description of the upgrade procedures for each specific component. Please take note of the warning and safety information indicated by the “” symbol.

The balance of this chapter reviews the computer's technical specifications and features.

## Introduction

# Specifications



### Latest Specification Information

The specifications listed here are correct at the time of sending them to the press. Certain items (particularly processor types/speeds) may be changed, delayed or updated due to the manufacturer's release schedule. Check with your service center for more details.



### CPU

The CPU is not a user serviceable part. Accessing the CPU in any way may violate your warranty.

## Processor Options

### Intel® Core™ i7 Processor

#### i7-8550U (1.80GHz)

6MB Smart Cache, 14nm, DDR4-2400MHz, TDP 15W

### Intel® Core™ i5 Processor

#### i5-8250U (1.60GHz)

6MB Smart Cache, 14nm, DDR4-2400MHz, TDP 15W

### Intel® Core™ i3 Processor

#### i3-7100U (2.40GHz)

3MB Smart Cache, 14nm, DDR4-2400MHz, TDP 15W

## BIOS

64Mb SPI Flash ROM

AMI BIOS

## Memory

Two 260 Pin SO-DIMM Sockets Supporting **DDR4 2400 MHz** Memory

Memory Expandable up to 32GB

Compatible with 4GB, 8GB or 16GB Modules

(The real memory operating frequency depends on the FSB of the processor.)

## LCD Options

15.6" (39.62cm), 16:9, HD (1366x768)/FHD (1920x1080)  
(Thickness: 3.2mm)

## Video Adapter

**Intel HD Graphics 620** (for i3-7100U only)

Dynamic Frequency

Intel Dynamic Video Memory Technology

Microsoft DirectX®12 Compatible

**Intel UHD Graphics 620** (for i7-8550U, i5-8250U only)

Dynamic Frequency

Intel Dynamic Video Memory Technology

Microsoft DirectX®12 Compatible

## Storage

One Changeable 2.5" 7mm (h) SATA HDD/SSD

**(Factory Option)** One 9.5mm/9.0mm(h) Optical Device Type Drive (DVD Writer)

Or

**(Factory Option)** Dummy ODD

Or

**(Factory Option)** 7mm (h) 2nd HDD/SSD Caddy

**(Factory Option)** One M.2 **SATA/PCIe Gen3 x4** Solid State Drive (SSD)

## Pointing Device

Built-in Touchpad

## Keyboard

Full-size keyboard (with numeric keypad)

Or

**(Factory Option)** Full-size **Illuminated White-LED** Keyboard (with numeric keypad)

## Audio

High Definition Audio Compliant Interface

2 \* Built-In Speakers

Built-In Microphone

**(Factory Option)** Built-In Array Microphone

## Security

Security (Kensington® Type) Lock Slot

BIOS Password

Intel PTT for Systems Without TPM Hardware

**(Factory Option)** TPM 2.0

**M.2 Slots**

Slot 1 for **WLAN and Bluetooth** Combo Module

Slot 2 for **SATA/PCIe Gen3 x4 SSD**

(Factory Option) Slot 3 for **3G/4G** Module

**Interface**

Two USB 2.0

One USB 3.0 (USB 3.1 Gen 1) Type-A Port

One USB 3.0 (USB 3.1 Gen 1)

Or

(Factory Option) One USB 3.1 Gen 2

Three USB 3.0 (USB 3.1 Gen 1) Type-A Ports

One HDMI-Out Port

One External Monitor Port

One Microphone-In Jack

One Headphone-Out Jack

One RJ-45 LAN Jack

One DC-in Jack

**USB 3.1 Gen 2**

Note that when a single USB device is plugged in to a USB 3.1 Gen 2 port the data transfer speed will be 10Gbps, however when two devices are plugged in to both USB 3.1 Gen 2 ports, this bandwidth will be shared between the ports.

**Card Reader**

Embedded Multi-In-1 Card Reader

MMC (MultiMedia Card) / RS MMC

SD (Secure Digital) / Mini SD / SDHC/ SDXC

**Communication**

Built-In 10/100/1000Mb Base-TX Ethernet LAN

1.0M HD PC Camera Module

(Factory Option) **3G** or **4G** M.2 Module

**WLAN/ Bluetooth M.2 Modules:**

(Factory Option) Intel® Wireless-AC 8265 Wireless LAN (802.11ac) + Bluetooth

(Factory Option) Intel® Wireless-AC 3168 Wireless LAN (802.11ac) + Bluetooth

**Power**

Full Range AC/DC Adapter

AC Input: 100 - 240V, 50 - 60Hz

DC Output: 19V, 2.1A (**40W**)

(Factory Option) Removable 4 Cell Smart Lithium-Ion Battery Pack, 31WH

**Environmental Spec****Temperature**

Operating: 5°C - 35°C

Non-Operating: -20°C - 60°C

**Relative Humidity**

Operating: 20% - 80%

Non-Operating: 10% - 90%

**Dimensions & Weight**

377mm (w) \* 259mm (d) \* 24.8mm (h)

(Height Excluding Battery Area)

**2.2kg** (Barebone with 31WH Battery)

## Introduction

*Figure 1*  
**Top View**

1. PC Camera
2. \*PC Camera LED  
*\*When the PC camera is in use, the LED will be illuminated in white.*
3. Built-In Microphone
4. LCD
5. Power Button
6. Keyboard
7. Touchpad & Buttons

## External Locator - Top View with LCD Panel Open



## External Locator - Front & Right Side Views

FRONT VIEW



*Figure 2*  
**Front View**

1. LED Indicators
2. Multi-in-1 Card Reader

RIGHT SIDE VIEW



*Figure 3*  
**Right Side View**

1. Headphone-Out Jack
2. Microphone-In Jack
3. USB 2.0
4. ODD Bay
5. Emergency Eject Hole
6. Security Lock Slot

## Introduction

### External Locator - Left Side & Rear View

*Figure 4*  
**Left Side View**

1. DC-In Jack
2. External Monitor Port
3. RJ-45 LAN Jack
4. Vent
5. HDMI-Out Port
6. USB 3.0/3.1 Port
7. USB 3.0 (USB 3.1 Gen 1) Type-C Port

LEFT SIDE VIEW




*Figure 5*  
**Rear View**

1. Battery

REAR VIEW



## External Locator - Bottom View



*Figure 6*  
**Bottom View**

1. Battery
2. Vent
3. Speakers




### **Overheating**

To prevent your computer from overheating, make sure nothing blocks any vent while the computer is in use.



*Figure 7*  
Mainboard Top  
Key Parts

## Mainboard Overview - Top (Key Parts)






## Mainboard Overview - Bottom (Key Parts)

*Figure 8*  
**Mainboard Bottom  
Key Parts**

1. KBC-ITE IT8587
2. CPU
3. Memory Slots  
DDR4 SO-DIMM
4. CMOS Battery




## Introduction

*Figure 9*  
**Mainboard Top  
Connectors**

1. DC-In Jack
2. External Monitor Port
3. RJ-45 LAN Jack
4. HDMI-Out Port
5. USB Port 3.0/3.1
6. USB Port 3.0/3.1 Type C Port
7. Keyboard Cable Connector


## Mainboard Overview - Top (Connectors)





*Figure 10*  
**Mainboard Bottom  
Connectors**

1. 3G/LTE Card Connector
2. LID Connector
3. CCD Connector
4. ODD Connector
5. HDD Connector
6. Speaker Connector
7. Multi-in-1 Card Reader
8. LCD Cable Connector
9. WLAN Connector
10. SIM Card Reader
11. Battery Connector






# Chapter 2: Disassembly



## Overview

This chapter provides step-by-step instructions for disassembling the *N750WU* / *N751WU* series notebook's parts and subsystems. When it comes to reassembly, reverse the procedures (unless otherwise indicated).

We suggest you completely review any procedure before you take the computer apart.

Procedures such as upgrading/replacing the RAM, optical device and hard disk are included in the User's Manual but are repeated here for your convenience.

To make the disassembly process easier each section may have a box in the page margin. Information contained under the figure # will give a synopsis of the sequence of procedures involved in the disassembly procedure. A box with a  lists the relevant parts you will have after the disassembly process is complete. **Note:** The parts listed will be for the disassembly procedure listed ONLY, and not any previous disassembly step(s) required. Refer to the part list for the previous disassembly procedure. The amount of screws you should be left with will be listed here also.

A box with a  will also provide any possible helpful information. A box with a  contains warnings.

An example of these types of boxes are shown in the sidebar.

  
Information

Warning


## Disassembly

**NOTE:** All disassembly procedures assume that the system is turned **OFF**, and disconnected from any power supply (the battery is removed too).

### Maintenance Tools

The following tools are recommended when working on the notebook PC:

- M3 Philips-head screwdriver
- M2.5 Philips-head screwdriver (magnetized)
- M2 Philips-head screwdriver
- Small flat-head screwdriver
- Pair of needle-nose pliers
- Anti-static wrist-strap



### Connections

Connections within the computer are one of four types:

Locking collar sockets for ribbon connectors

To release these connectors, use a small flat-head screwdriver to gently pry the locking collar away from its base. When replacing the connection, make sure the connector is oriented in the same way. The pin1 side is usually not indicated.

Pressure sockets for multi-wire connectors

To release this connector type, grasp it at its head and gently rock it from side to side as you pull it out. Do not pull on the wires themselves. When replacing the connection, do not try to force it. The socket only fits one way.

Pressure sockets for ribbon connectors

To release these connectors, use a small pair of needle-nose pliers to gently lift the connector away from its socket. When replacing the connection, make sure the connector is oriented in the same way. The pin1 side is usually not indicated.

Board-to-board or multi-pin sockets

To separate the boards, gently rock them from side to side as you pull them apart. If the connection is very tight, use a small flat-head screwdriver - use just enough force to start.

## Maintenance Precautions

The following precautions are a reminder. To avoid personal injury or damage to the computer while performing a removal and/or replacement job, take the following precautions:

1. **Don't drop it.** Perform your repairs and/or upgrades on a stable surface. If the computer falls, the case and other components could be damaged.
2. **Don't overheat it.** Note the proximity of any heating elements. Keep the computer out of direct sunlight.
3. **Avoid interference.** Note the proximity of any high capacity transformers, electric motors, and other strong magnetic fields. These can hinder proper performance and damage components and/or data. You should also monitor the position of magnetized tools (i.e. screwdrivers).
4. **Keep it dry.** This is an electrical appliance. If water or any other liquid gets into it, the computer could be badly damaged.
5. **Be careful with power.** Avoid accidental shocks, discharges or explosions.
  - Before removing or servicing any part from the computer, turn the computer off and detach any power supplies.
  - When you want to unplug the power cord or any cable/wire, be sure to disconnect it by the plug head. Do not pull on the wire.
6. **Peripherals** – Turn off and detach any peripherals.
7. **Beware of static discharge.** ICs, such as the CPU and main support chips, are vulnerable to static electricity. Before handling any part in the computer, discharge any static electricity inside the computer. When handling a printed circuit board, do not use gloves or other materials which allow static electricity buildup. We suggest that you use an anti-static wrist strap instead.
8. **Beware of corrosion.** As you perform your job, avoid touching any connector leads. Even the cleanest hands produce oils which can attract corrosive elements.
9. **Keep your work environment clean.** Tobacco smoke, dust or other air-born particulate matter is often attracted to charged surfaces, reducing performance.
10. **Keep track of the components.** When removing or replacing any part, be careful not to leave small parts, such as screws, loose inside the computer.

## Cleaning

Do not apply cleaner directly to the computer, use a soft clean cloth.

Do not use volatile (petroleum distillates) or abrasive cleaners on any part of the computer.

**(For Computer Models Supplied with Light Blue Cleaning Cloth)** Some computer models in this series come supplied with a light blue cleaning cloth. To clean the computer case with this cloth follow the instructions below.

- Power off the computer and peripherals.
- Disconnect the AC/DC adapter from the computer.
- Use a little water to dampen the cloth slightly.
- Clean the computer case with the cloth.
- Dry the computer with a dry cloth, or allow it time to dry before turning on.
- Reconnect the AC/DC adapter and turn the computer on.



### Power Safety Warning

Before you undertake any upgrade procedures, make sure that you have turned off the power, and disconnected all peripherals and cables (including telephone lines and power cord). It is advisable to also remove your battery in order to prevent accidentally turning the machine on.

## Disassembly Steps

The following table lists the disassembly steps, and on which page to find the related information. **PLEASE PERFORM THE DISASSEMBLY STEPS IN THE ORDER INDICATED.**

### To remove the Battery:

1. Remove the battery *page 2 - 5*

### To remove the Keyboard:

1. Remove the battery *page 2 - 5*
2. Remove the keyboard *page 2 - 6*

### To remove the HDD:

1. Remove the battery *page 2 - 5*
2. Remove the keyboard *page 2 - 6*
3. Remove the HDD *page 2 - 7*

### To remove the 2nd HDD:

1. Remove the battery *page 2 - 5*
2. Remove the keyboard *page 2 - 6*
3. Remove the 2nd HDD *page 2 - 9*

### To remove the Optical Device:

1. Remove the battery *page 2 - 5*
2. Remove the keyboard *page 2 - 6*
3. Remove the HDD *page 2 - 7*
4. Remove the Optical Device *page 2 - 11*

### To remove the System Memory:

1. Remove the battery *page 2 - 5*
2. Remove the keyboard *page 2 - 6*
3. Remove the HDD *page 2 - 7*
4. Remove the system memory *page 2 - 11*

### To remove the Wireless LAN Module:

1. Remove the battery *page 2 - 5*
2. Remove the keyboard *page 2 - 6*
3. Remove the HDD *page 2 - 7*
4. Remove the WLAN *page 2 - 13*

### To remove the 3G:

1. Remove the battery *page 2 - 5*
2. Remove the keyboard *page 2 - 6*
3. Remove the HDD *page 2 - 7*
4. Remove the 3G *page 2 - 15*

### To remove the M.2 SSD:

1. Remove the battery *page 2 - 5*
2. Remove the keyboard *page 2 - 6*
3. Remove the HDD *page 2 - 7*
4. Remove the SSD *page 2 - 16*
5. Install the SSD *page 2 - 17*


### To remove the CCD Module:

1. Remove the battery *page 2 - 5*
2. Remove the keyboard *page 2 - 6*
3. Remove the HDD *page 2 - 7*
4. Remove the CCD module *page 2 - 18*



## Removing the Battery

1. Turn **off** the computer, turn it over.
2. Slide the latch **1** in the direction of the arrow (**Figure 1a**).
3. Slide the latch **2** in the direction of the arrow, and hold it in place (**Figure 1b**).
4. Turn the battery **3** in the direction of the arrow **4** and lift it out (**Figure 1c**).
5. Insert a new battery **3** by aligning the battery to the pins **5** & **6** (**Figure 1d**).
6. Turn the battery **3** in the direction of the arrow **7** (**Figure 1e**).
7. Slide the latch **8** in the direction of the arrow to lock it in place (**Figure 1f**).



*Figure 1*  
**Battery Removal**

- Slide the latch and hold it in place.
- Turn the battery in the direction of the arrow.
- Lift the battery out.
- Insert a new battery by aligning it to the pins.
- Turn the battery in the direction of the arrow.
- Lock the latch in place.

3. Battery


## Disassembly

*Figure 2*  
**Keyboard Removal**

- Remove the screws.
- Release the keyboard by pressing at point ③.
- Disconnect the keyboard ribbon cable from the locking collar socket.
- Remove the keyboard.

## Removing the Keyboard

- Turn **off** the computer, turn it over to remove the battery ([page 2 - 5](#)).
- Remove screws ① - ② from the bottom case ([Figure 2a](#)).
- Open it up with the LCD on a flat surface before pressing at point ③ to release the keyboard module while releasing the keyboard in the direction of the arrow ④ as shown ([Figure 2c](#)).
- Carefully lift the keyboard ⑤ up, being careful not to bend the keyboard ribbon cable ⑥. Disconnect the keyboard ribbon cable from the locking collar socket ⑦ ([Figure 2d](#)).
- Carefully lift up the keyboard ⑤ off the computer ([Figure 2e](#)).
- Reverse the process to install the keyboard (do not forget to replace all the screws).



5. Keyboard


- 2 Screws

## Removing the Hard Disk Drive

The hard disk drive can be taken out to accommodate other 2.5" serial (SATA) hard disk drives with a height of 7.0mm (h). Follow your operating system's installation instructions, and install all necessary drivers and utilities (as outlined in **Chapter 4 of the User's Manual**) when setting up a new hard disk.

### Hard Disk Upgrade Process

1. Turn **off** the computer, turn it over to remove the battery ([page 2 - 5](#)) and keyboard ([page 2 - 6](#)).
2. Remove screws **1** - **3** underneath the keyboard ([Figure 3a](#)).
3. Remove screws **4** - **12** ([Figure 3b](#)).
4. Lift the bottom cover **13** up from point **14** ([Figure 3c](#)).
5. The hard disk drive will be visible at point **15** ([Figure 3d](#)).



15. Bottom Cover

- 12 Screws

*Figure 3*  
**HDD Assembly Removal**

- a. Remove the screws.
- b. Remove the screws.
- c. Remove the bottom cover.
- d. Locate the HDD assembly.



#### HDD System Warning

New HDD's are blank. Before you begin make sure:

You have backed up any data you want to keep from your old HDD.

You have all the CD-ROMs and FDDs required to install your operating system and programs.




If you have access to the internet, download the latest application and hardware driver updates for the operating system you plan to install. Copy these to a removable medium.

## Disassembly

*Figure 4*  
**HDD Assembly  
Removal (cont'd.)**

- d. Remove the screw.
- e. Slightly lift and pull the HDD assembly in the direction of the arrow.
- f. Lift the HDD assembly out of the bay.
- g. Remove the screws and HDD bracket.

- 6. Remove the screw 16 from the hard disk assembly (Figure 4d).
- 7. Slightly lift and pull the hard disk assembly in the direction of arrow 17 (Figure 4e).
- 8. Lift the hard disk assembly 18 out of the bay 19 (Figure 4f).
- 9. Remove the screws 20 - 21 and the HDD bracket 22 from the hard disk 23 (Figure 4g).
- 10. Reverse the process to install a new hard disk (do not forget to replace all the screws and bottom cover).



18. HDD Assembly  
22. HDD Bracket  
23. HDD

- 3 Screws




## Removing the 2nd Hard Disk from Caddy Bay

1. Turn **off** the computer, remove the battery ([page 2 - 5](#)), and bottom case ([page 2 - 7](#)).
2. Carefully push out the caddy bay **1** out in the direction of the arrow **2** ([Figure 5a](#)).
3. Remove screws **3** - **4** (will depends on the HDD type) from the bottom of the caddy bay.
4. Remove screws **5** - **6** to release the hard disk assembly ([Figure 5b](#)).
5. Lift the hard disk assembly **7** out of the caddy bay **8** ([Figure 5c](#)).
6. Separate the hard disk **9** and connector board **10** ([Figure 5d](#)).
7. Reverse the process to install a new hard disk.
8. Restart the computer to allow it to automatically detect the new device.

*Figure 5*  
**2nd HDD Removal**

- a. Push the caddy bay out off the computer.
- b. Remove the screws.
- c. Lift the hard disk assembly out of the caddy bay
- d. Separate the hard disk and connector.



1. Dummy Bay  
7. HDD Assembly  
9. Hard Disk  
10. Connector Board
- 4 Screws


## Disassembly

*Figure 6*  
**Optical Device  
Removal**

- a. Push the optical device out off the computer.
- b. Pry the bezel off the optical device.
- c. Separate the bezel and optical device
- d. Install the front bezel.

## Removing the Optical (CD/DVD) Device

1. Turn **off** the computer, remove the battery ([page 2 - 5](#)), and bottom case ([page 2 - 7](#)).
2. Carefully push out the optical device **1** out of the bay in the direction of the arrow **2** ([Figure 6a](#)).
3. Carefully pry the bezel **4** off the optical device at point **3** ([Figure 6b](#)).
4. Separate the bezel **4** and the optical device ([Figure 6d](#)).
5. Reverse the process to attach the front bezel **4** with the new optical device at point **5** ([Figure 6d](#)).
6. Insert the new device and carefully slide it into the computer (the device only fits one way. DO NOT FORCE IT; The screw holes should line up). Replace the bottom cover and tighten the screws.
7. Restart the computer to allow it to automatically detect the new device.



1. Optical Device
4. Bezel Cover

## Removing the System Memory (RAM)

The computer has two memory sockets for 260 pin Small Outline Dual In-line Memory Modules (SO-DIMM) supporting DDR4 Up to 2400 MHz. The main memory can be expanded up to 32GB. The total memory size is automatically detected by the POST routine once you turn on your computer.


### Memory Upgrade Process

1. Turn **off** the computer, turn it over to remove the battery ([page 2 - 5](#)) and bottom cover ([page 2 - 7](#)).
2. The RAM modules will be visible at point **1** on the mainboard ([Figure 7b](#)).
3. Gently pull the two release latches (**2** & **3**) on the sides of the memory socket in the direction indicated by the arrows ([Figure 7b](#)).
4. The RAM module **4** will pop-up ([Figure 7c](#)), and you can then remove it.


*Figure 7*  
**RAM Module Removal**

- a. The RAM modules will be visible at point **1** on the mainboard.
- b. Pull the release latches.
- c. Remove the module.


a.



b.



c.



#### Single Memory Module Installation

If your computer has a single memory module, then insert the module into the **Channel 0 (JDIMM1 / RAM1)** socket.



#### Contact Warning

Be careful not to touch the metal pins on the module's connecting edge. Even the cleanest hands have oils which can attract particles, and degrade the module's performance.



4. RAM Module

## Disassembly


---

5. Pull the latches to release the second module if necessary.
6. Insert a new module holding it at about a 30° angle and fit the connectors firmly into the memory slot.
7. The module will only fit one way as defined by its pin alignment. Make sure the module is seated as far into the slot as it will go. DO NOT FORCE IT; it should fit without much pressure.
8. Replace the bottom case and the screws (see [page 2 - 7](#)).
9. Restart the computer to allow the BIOS to register the new memory configuration as it starts up.



## Removing the Wireless LAN Module

1. Turn **off** the computer, turn it over to remove the battery ([page 2 - 5](#)) and bottom cover ([page 2 - 7](#)).
2. The Wireless LAN module will be visible at point **1** on the mainboard ([Figure 8a](#)).
3. Carefully disconnect the cables **2** & **3**, and then remove the screw **4** ([Figure 8b](#)).
4. The Wireless LAN module **5** ([Figure 8c](#)) will pop-up, and you can remove it from the computer.



*Figure 8*  
**WLAN Module Removal**

- a. Locate the WLAN.
- b. Disconnect the cable and remove the screw.
- c. The WLAN module will pop up and lift it out of the computer.

Note: Make sure you reconnect the antenna cable to the “1 + 2” socket ([Figure 8b](#)).



5. Wireless LAN Module

- 1 Screw

## Disassembly

### Wireless LAN, Combo, 3G & LTE Module Cables

Note that the cables for connecting to the antennae on WLAN, WLAN & Bluetooth Combo, 3G and LTE modules are not labelled. The cables/covers (each cable will have either a black or transparent cable cover) are color coded for identification as outlined in the table below.



Module Type	Antenna Type	Cable Color	Cable Cover Type
WLAN/WLAN & Bluetooth Combo	WM 1	Black	Transparent
	WM 2	Black	White
LTE Broadband	LTE 1	Black	Black
	LTE 2	Black	Blue

Cable 1 is usually connected to antenna 1 (Main) on the module, and cable 2 to antenna 2 (Aux).

## Removing the 3G Module

### 3G Module Removal Procedure

1. Turn **off** the computer, turn it over to remove the battery ([page 2 - 5](#)) and bottom cover ([page 2 - 7](#)).
2. The module will be visible at point **1** on the mainboard ([Figure 9a](#)).
3. Carefully disconnect the cables **2** & **3**, and then remove the screw **4** from the module ([Figure 9b](#)).
4. The module **5** will pop-up ([Figure 9c](#)).
5. Lift the module **5** up and off the computer ([Figure 9d](#)).



*Figure 9*  
**3G Module Removal**

- Locate the module.
- Disconnect the cables and remove the screw.
- The module will pop up.
- Lift the module up and off the socket



3.M2 SATA-1 Module

- 1 Screw

## Disassembly



*Figure 10*  
**M.2 SSD Module Removal**

- a. Locate the M.2 SSD.
- b. Remove the screw.
- c. The M.2 SSD module will pop up.

## Removing and Installing the M.2 SSD Module

### m.2 SSD Removal Procedure

1. Turn **off** the computer, turn it over to remove the battery ([page 2 - 5](#)) and bottom cover ([page 2 - 7](#)).
2. The M.2 SSD module will be visible at point **1** on the mainboard ([Figure 10a](#)).
3. Remove the screw **2** ([Figure 10b](#)).
4. The M.2 SSD module **3** ([Figure 10c](#)) will pop-up, and you can remove it from the computer.



3.M2 SATA-1 Module


- 1 Screw



## M.2 SSD Installation Procedure

1. Place the thermal pad **1** on the bottom case as shown (**Figure 11a**).
2. Insert the module **2** in the computer (**Figure 11b**).
3. Tighten the screw **3** to secure it in place (**Figure 11c**).

a.



b.



c.



*Figure 11*  
**M.2 SSD Module Installation**

- a. Place the thermal pad.
- b. Insert the module.
- c. Tighten the screw.



### Thermal Pad

Be sure to place the thermal pad's adhesive side down onto the mainboard surface.

The thermal pad's thickness differ for different M.2 SSD module:

- For module with chip, use 2.5mm thick thermal pad.
- For module without chip, use 3.5mm thick thermal pad.



1. Thermal Pad
2. M.2 SSD Module

- 1 Screw



## Disassembly

Figure 12  
CCD Removal

- Remove cover and screws. Then run your fingers around the inner frame of the LCD panel at the points indicated by the arrows.
- Push the LCD front panel upwards before carefully lifting it up.
- Remove the LCD front cover.

## Removing the CCD

- Turn **off** the computer, turn it over to remove the battery ([page 2 - 5](#)).
- Lay the computer down on a flat surface with the top case up forming a 90 degree angle. Carefully remove the rubber covers **1** - **2** and screws **3** - **4**.
- Run your fingers around the inner frame of the LCD panel at the points as indicated by the arrows **5** - **8** ([Figure 12a](#)).
- Push the LCD front cover **9** upwards before carefully lifting it up ([Figure 12b](#)).
- Remove the LCD front cover **9** ([Figure 12c](#)).



9. LCD Front Cover

- 2 Screws


*Figure 13*  
**CCD Removal  
(cont'd)**

- d. Disconnect the cable.
- e. Remove the CCD module.

d.



e.



7. CCD Module





---

# Appendix A:Part Lists

This appendix breaks down the *N750WU* / *N751WU* series notebook's construction into a series of illustrations. The component part numbers are indicated in the tables opposite the drawings.

**Note:** This section indicates the *manufacturer's* part numbers. Your organization may use a different system, so be sure to cross-check any relevant documentation.

**Note:** Some assemblies may have parts in common (especially screws). However, the part lists DO NOT indicate the total number of duplicated parts used.

**Note:** Be sure to check any update notices. The parts shown in these illustrations are appropriate for the system at the time of publication. Over the product life, some parts may be improved or re-configured, resulting in *new* part numbers.

---

## Part List Illustration Location

The following table indicates where to find the appropriate part list illustration.

*Table A - 1*  
**Part List Illustration  
Location**

Part	
Top	<i>page A - 3</i>
Bottom	<i>page A - 4</i>
LCD	<i>page A - 5</i>
HDD	<i>page A - 6</i>
HDD Caddy	<i>page A - 7</i>
DVD	<i>page A - 8</i>
MB	<i>page A - 9</i>

## A. Part Lists




Top A 3

**Top A - 3**


Bottom

Figure A - 2  
Bottom



ITEM	PART NAME	PART NO	REMARK
1	W/ 1.5" HAV/200V/200V KIP 001000 000000 000000 000000 000000	6-87-N750S-3CF2	
1	W/ 1.5" HAV/200V/200V KIP 001000 000000 000000 000000 000000	6-87-N750S-4EB2	
1	W/ 1.5" HAV/200V/200V KIP 001000 000000 000000 000000 000000	6-87-N750S-41C00	
1	W/ 1.5" HAV/200V/200V KIP 001000 000000 000000 000000 000000	6-87-N750S-31C00	
2	BOTTOM CASE MODULE N750WU	6-39-N75W3-011	
3	SCREW M2.5*6L K BZ ICT NY	6-35-82125-6RA	
4	PRODUCT LABEL FOR N750WU	6-45-N750WU03-010	
4	PRODUCT LABEL FOR N751WU	6-45-N751WU03-010	
5	SCREW M2*5L K1T=0.8 D=4.0 BK/Z ICT NY	6-35-B6120-SR0	
6	DUMMY 3D NON PUSH TYPE PC CASE (C7200P-70100) V97000W	6-42-W9708-030	
7	W/O HDD ASS'Y N750BU	6-79-N750BU02-000	
7	2ND HDD CADDY ASS'Y W/O HDD N750BU	6-79-N750BU0J-030	
7	2ND HDD CADDY ASS'Y W/HDD N750BU	6-79-N750BU0J-040	
7	SATA DVD SUPER MULTI BX ASS'Y N750BU	6-79-N750BU00-001	
8	HDD PC MYLAR 0.5T N750HU	6-40-N75H2-031	ONLY FOR 9.0MM HDD

LCD





ITEM	PART NAME	PART NO	REMARK
1	LCD PROTECT MYLAR BOPP N650DU	6-40-N6508-040	
2	CCD LENS PMMA N750BU	6-42-N7501-010	
3	FRONT COVER MODULE N750BU	6-39-N7501-012	
4	SCREW M2X3L K1 BZ ICT NY (DD=H4.5,DT=0.4)	6-35-B6120-3RD	
5	LED 15.6" FHD/IPS/CEP LG LP156WF6-SPK3 QHD 4LED 32NM	6-50-LB232-L08	
5	LED 15.6" FHD/IPS/CEP LG LP156WF6-SPK3 QHD 4LED 32NM	6-50-LB232-L04	
5	LED 15.6" HD (CEIP) AU B156XTN07.1 C32NM LED	6-50-LB132-G04	
5	LED 15.6" FHD/CEIP AU B156XTN03.8 QH/V460 LED 32NM	6-50-LB232-G18	
5	LED 15.6" FHD/IPS/PM/NDM GT/CEIP LG LP156WF6-SPK6 4LED32NM	6-50-LB232-L010	
6	HINGE L (SK7+SGCC) SNR N750BU	6-33-N7501-0L2	
7	BVC CAMERA BEZEL FOR DIFFERENT CAMERA IN H DUSTY KEYS FINGER WHITE-LED V49-MC	6-88-W51PC-5110	OPTION
7	BVC CAMERA BEZEL FOR DIFFERENT CAMERA IN H DUSTY KEYS FINGER WHITE-LED V49-MC	6-88-N650C-4910	OPTION
7	BVC CAMERA BEZEL FOR DIFFERENT CAMERA IN H DUSTY KEYS FINGER WHITE-LED V49-MC	6-88-W51PC-5100	OPTION
7	BVC CAMERA BEZEL FOR DIFFERENT CAMERA IN H DUSTY KEYS FINGER WHITE-LED V49-MC	6-88-N650C-4900	OPTION
7	BVC CAMERA BEZEL FOR DIFFERENT CAMERA IN H DUSTY KEYS FINGER WHITE-LED V49-MC	6-88-W65DC-5100	OPTION
7	BVC CAMERA BEZEL FOR DIFFERENT CAMERA IN H DUSTY KEYS FINGER WHITE-LED V49-MC	6-88-P775C-4901	OPTION
7	BVC CAMERA BEZEL FOR DIFFERENT CAMERA IN H DUSTY KEYS FINGER WHITE-LED V49-MC	6-88-W65DC-5110	OPTION
7	BVC CAMERA BEZEL FOR DIFFERENT CAMERA IN H DUSTY KEYS FINGER WHITE-LED V49-MC	6-88-N850C-4901	OPTION
7	BVC CAMERA BEZEL FOR DIFFERENT CAMERA IN H DUSTY KEYS FINGER WHITE-LED V49-MC	6-88-N770C-4900	OPTION
7	BVC CAMERA BEZEL FOR DIFFERENT CAMERA IN H DUSTY KEYS FINGER WHITE-LED V49-MC	6-88-N770C-4910	OPTION
8	ANTENNA PEEL W/IN W/ET W/2 PCB AL 24G/50HZ W/2-50MM N750BU	6-23-7N750-020	
9	ANTENNA PEEL W/IN W/ET W/2 PCB AL 24G/50HZ W/2-50MM N750BU	6-23-7N650-010	
10	BACK COVER MODULE N750BU	6-39-N7501-023	
10	LCD BACK COVER MODULE N751BU	6-39-N7511-021	
11	SCREW M2.5X6L K BZ ICT NY	6-35-82125-6RA	
12	SCREW M2.5X2.5L K1 BK/Z ICT NY(08,T=0.6)	6-35-B6125-2R5	
13	FRONT COVER SCREW MYLAR/PPC(SH46/SH54/SH125) N750BU	6-40-N1501-010	
14	WIRE CABLE FOR CEP 200MM Q1 FV 30PIN (CM/TOL CON49-4022P) N750BU	6-43-N7501-012-2C	
15	HINGE R (SK7+SGCC) SNR N750BU	6-33-N7501-0R2	
16	WIRE CABLE FOR CCD D-MIC 500MM 3.3V BP (CMD) N750BU	6-43-N250T-011-2	
17	ANTENNA PEEL W/IN W/ET W/2 PCB AL 24G/50HZ W/2-50MM N750BU	6-23-7N550-011	
18	FRONT COVER GLUE UBD (NETTO 5000 330X40X1.5) FOR N750BU	6-40-W6551-010	
19	SPONGE 60X8X2.65T SM55+G9000 FOR N750BU	6-47-0019A-75E	FOR N75XBU/N75XHU

Figure A - 3  
LCD

HDD



Figure A - 4  
HDD



ITEM	PART	NAME	PART NO	REMARK
1	SCREW	M3*2.5L KI NI ICT NY	6-35-B1130-2R5	
2	HDD BKT	7MM SECC T=0.5 N250LU	6-33-N250J-011	
3	SCREW	M2*3L KI BZ ICT NY (DD=Ø4.5,DT=0.4)	6-35-B6120-3RD	



# HDD Caddy





ITEM	PART NAME	PART NO	REMARK
1	SCREW M2*3L KI BZ ICT NY (DD=M4.5,DT=0.4)	6-35-B6120-3RD	
2	SCREW M2*2L KI BK/Z ICT NY(Ø8,T=0.6)	6-35-B6120-2RE	
3	CADDY BAY BOARD V2.0 N750BU	6-77-N750N-D02	FOR N750BU
3	CADDY BAY BOARD V1.0 N750HU	6-77-N75HN-D01	FOR N750HU
3	ODD TO HDD BOARD V2.0 N750WU	6-77-N75WN-D02	FOR N750WU
4	ODD BRACKET SECC W547BL	6-33-W547Z-011	
5	SCREW M3*2.5L KI NI ICT NY	6-35-B1130-2R5	
6	DUMMY ODD MODULE N750BU	6-42-N750Z-102	
7	ODD BEZEL MODULE N750BU	6-42-N750Z-202	


Figure A - 5  
HDD Caddy

DVD

Figure A - 6  
DVD



ITEM	PART NAME	PART NO	REMARK
1	SCREW M2X3L KI BZ ICT NY (DD=04.5,DT=0.4)	6-35-B6120-3RD	
2	ODD BRACKET SECC W547BL	6-33-W547Z-011	
3	SATA DVD SUPER MULTI 5 1/4" BK 95MM DA-BASHOX F/W 08SL H/W 01 Q/WN 01 PLDS	6-85-A088X-L04	FOR PLDS
3	SATA DVD SUPER MULTI 5 1/4" BK 95MM GUDON ROM VER 1.00 Q/WN 100 HLDS	6-85-A088X-502	FOR HLDS
3	SATA DVD DVD_DUAL 5 1/4" BK 95MM DA-BASH PLDS	6-85-A088X-L06	FOR PLDS
3	SATA DVD SUPER MULTI 5 1/4" BK 95MM GUDON HLDS	6-85-A088X-503	FOR HLDS
3	SATA DVD WRITER 5 1/4" BK 95MM GUDON ROM VER 1.00 Q/WN 100 HLDS	6-85-A088X-504	FOR HLDS
3	SATA DVD WRITER 5 1/4" BK 95MM DU-BASH 07/0600M H/W00 PLDS	6-85-A088X-L05	FOR PLDS
4	ODD BEZEL MODULE N750BU	6-42-N750Z-202	
5	SUPER MULTI ODD BEZEL LABEL N650DU	6-45-N650Q-020	



ITEM	PART NAME	PART NO	REMARK
1	MAIN BOARD(CPU:V5-850U/L60 V20M ICPYWA/TEJWA/D TPJUS330 N750U)	6-77-N750WU00-D02A-5F	
1	MAIN BOARD(CPU:V3-700U/L60 V20M ICPYWA/D TPJLLEJ330 N750U)	6-77-N750WU00-D02A-7B	
1	MAIN BOARD(CPU:V3-700U/L60 V20M ICPYWA/TEJUS330W/D TPO N750U)	6-77-N750WU00-D02A-4D	
1	MAIN BOARD(CPU:V7-850U/L60 V20M ICPYWA/TEJUS330W/D TPO N750U)	6-77-N750WU00-D02A-4E	
2	SCREW M2x3L KI BZ ICT NY (D0=4.5,D1=0.4)	6-35-B6120-3RD	
3	WARRANTY CARD DUAL TPO INTEL SMART FEAR 3636AW D0 ACUT D142 R2 ZEN P50S	6-88-P65SF-4210	OPTION
3	WARRANTY CARD DUAL TPO INTEL SMART FEAR 3636AW D0 ACUT D142 R2 ZEN P50S	6-88-P65SF-4200	OPTION
4	SCREW M2x2L KI NI ICT NY (D0=4.5 ,T=0.5)	6-35-B1120-2RD	
5	CPU FAN MODULE <FORCECON> N550RC	6-31-N5502-102	
6	CPU HEATSINK MODULE N750WU	6-31-N75WN-101	
7	TAPE MYLAR (C),MYLAR M550J	6-40-M55J2-030	
8	W/O 3G RUBBER(R2624492)SILICON RUBBER P650SE	6-47-P6502-020	W/O 3G/LTE1
9	SCREW M2x2SL QH-25 B-50 STEEL ICT NY (FOR NGT CARDOCHARGE)	6-35-ZA120-2R5-1	FOR W/O M2 SSD
10	SSD M2 2280 512GB SAMSUNG EVO960-PH000 PCE GPM 3D TLC (FACTORY)	6-85-D515B-S05	OPTION
10	SSD M2 2280 256GB PHISON E5P56G1T2-S01 (SSD) SATA3 TLC	6-85-D51R6-H02	OPTION
10	SSD M2 2280 512GB CRUCIAL CT5256CR8SS04 (M320) SATA3 3D TLC	6-85-D51SR-100	OPTION
10	SSD M2 2280 256GB SAMSUNG 960 EVO (SSD) SATA3 GPM MLC 16253000	6-85-D51R6-200	OPTION
10	SSD M2 2280 256GB GIGABYTE G1009-256GB (G1009) SATA3 MLC	6-85-D51R6-400	OPTION
10	SSD M2 2280 512GB PHISON E5P56G1T2-E7 (CT) PCE GPM MLC	6-85-D515B-H00	OPTION
10	SSD M2 2280 1TB (GIGABYTE) INTEL 660P (GIGABYTE) GPM 3D TLC (FACTORY)	6-85-D511T-S00	OPTION
10	SSD M2 2280 1TB (GIGABYTE) INTEL 660P (GIGABYTE) GPM 3D TLC (FACTORY)	6-85-D511T-Z00	OPTION
10	SSD M2 2280 512GB PHISON E5P56G1T2-E7 (CT) PCE GPM MLC	6-85-D51R6-H04	OPTION
10	SSD M2 2280 256GB INTEL G1009-256GB (G1009) SATA3 MLC	6-85-D51R6-Z01	OPTION
10	SSD M2 2280 512GB INTEL 660P (GIGABYTE) GPM 3D TLC (FACTORY)	6-85-D5132-Z00	OPTION
11	SCREW M2x5L KI(T=0.8 D=4.0) BK/Z ICT NY	6-35-B6120-5RD	
12	TAPE MYLAR TRANSPARENT (204*104*0.05) P180HM	6-40-P1803-020	
13	THERMAL PAD RS300 35*10*1.25MM P775DM2	6-48-P7753-280	
14	W/O HUMANI MATEX 185W NGT CARD USB INTERFACE WITHOUT GPS S201U	6-88-S210W-8810	
14	LIT 4 HUMANI MATEX 185W NGT CARD USB INTERFACE WITHOUT GPS S201U	6-88-N5506-8801	
14	LIT 4 HUMANI MATEX 185W NGT CARD USB INTERFACE WITHOUT GPS S201U	6-88-W3306-8830	
15	BATTERY 3V 220MA BBBCR2032B (KTS)	6-23-6A2B2-030	

Figure A - 7  
HDD



# Appendix B: Schematic Diagrams

This appendix has circuit diagrams of the *N750WU* / *N751WU* notebook's PCB's. The following table indicates where to find the appropriate schematic diagram.

Diagram - Page	Diagram - Page	Diagram - Page
<i>System Block Diagram - Page B - 2</i>	<i>PCH 4/9 - Page B - 18</i>	<i>CCD, MIC, LID, I/O Connector - Page B - 34</i>
<i>Processor 1/6 - Page B - 3</i>	<i>PCH 5/9 - Page B - 19</i>	<i>KBC ITE IT8587 - Page B - 35</i>
<i>Processor 2/6 - Page B - 4</i>	<i>PCH 6/9 - Page B - 20</i>	<i>5V, 5VS, 3.3V, 3.3VS, 3.3VA - Page B - 36</i>
<i>Processor 3/6 - Page B - 5</i>	<i>PCH 7/9 - Page B - 21</i>	<i>VDD3, VDD5 - Page B - 37</i>
<i>Processor 4/6 - Page B - 6</i>	<i>PCH 8/9 - Page B - 22</i>	<i>DDR 1.2V/0.62VS, 2.5V - Page B - 38</i>
<i>Processor 5/6 - Page B - 7</i>	<i>PCH 9/9 - Page B - 23</i>	<i>VCC_CORE, VCCGT - Page B - 39</i>
<i>Processor 6/6 - Page B - 8</i>	<i>M.2 (WLAN, 3G, SSD) - Page B - 24</i>	<i>VCORE, VCCGT Output Stage - Page B - 40</i>
<i>DDR4 CHA SO_DIMM_0 - Page B - 9</i>	<i>Audio Codec - Page B - 25</i>	<i>VCCSA - Page B - 41</i>
<i>DDR4 CHB SO_DIMM_0 - Page B - 10</i>	<i>PS8330B - Page B - 26</i>	<i>VCCIO - Page B - 42</i>
<i>Panel, Inverter - Page B - 11</i>	<i>AR_TBT - Page B - 27</i>	<i>1.0DX_VCCSTG/VCCSFR_OC, 3.3VA - Page B - 43</i>
<i>VGA RTD2168 - Page B - 12</i>	<i>AR_Power - Page B - 28</i>	<i>Charger, AC-In - Page B - 44</i>
<i>Card Reader &amp; LAN RTL8411B - Page B - 13</i>	<i>ASM1543 - Page B - 29</i>	<i>Audio Board - Page B - 45</i>
<i>HDMI, RJ45, Fan, TPM - Page B - 14</i>	<i>TPS65982 - Page B - 30</i>	<i>Click Board - Page B - 46</i>
<i>PCH 1/9 - Page B - 15</i>	<i>Type C - Page B - 31</i>	<i>LID SW Board - Page B - 47</i>
<i>PCH 2/9 - Page B - 16</i>	<i>USB - Page B - 32</i>	<i>Caddy Bay Board - Page B - 48</i>
<i>PCH 3/9 - Page B - 17</i>	<i>HDD, ODD, LED - Page B - 33</i>	<i>Power Seq. - Page B - 49</i>


*Table B - 1*  
**SCHEMATIC  
DIAGRAMS**



## Version Note


The schematic diagrams in this chapter are based upon version 6-7P-N75W8-003. If your mainboard (or other boards) are a later version, please check with the Service Center for updated diagrams (if required).

**Sheet 1 of 48**  
**System Block**  
**Diagram**



## Processor 1/6

Sheet 2 of 48  
Processor 1/6






\_\_\_\_\_


## Processor 2/6

### 3. Schematic Diagrams

Sheet 3 of 48  
Processor 2/6



**Processor 3/6 B - 5**




\_\_\_\_\_


## Processor 4/6

## B. Schematic Diagrams

Sheet 5 of 48  
Processor 4/6




**Processor 5/6 B - 7**



## Processor 6/6

## B. Schematic Diagrams

Sheet 7 of 48  
Processor 6/6




[illegible]

## B.Schematic Diagrams




## DDR4 CHB SO\_DIMM\_0

Sheet 9 of 48  
DDR4 CHA SO-  
DIMM 0




# Panel, Inverter




Sheet 10 of 48  
Panel, Inverter

# VGA RTD2168

**Sheet 11 of 48**  
**VGA RTD2168**




## Card Reader &amp; LAN RTL8411B


Sheet 12 of 48  
Card Reader & LAN  
RTL8411B

# HDMI, RJ45, Fan, TPM

Sheet 13 of 48  
HDMI, RJ45, Fan, TPM



## PCH 1/9


Sheet 14 of 48  
PCH 1/9




Schematic Diagrams

PCH 2/9


Sheet 15 of 48  
PCH 2/9






**PCH 4/9**

Sheet 17 of 48  
PCH 4/9



# PCH 5/9




Sheet 18 of 48  
PCH 5/9


Schematic Diagrams

PCH 6/9


Sheet 19 of 48  
PCH 6/9



**PCH 7/9 B - 21**



Sheet 21 of 48  
PCH 8/9





The diagram illustrates a hardware test setup for a device, likely a microcontroller or SoC, with various components and connections.

**Top Section (A-D):** Shows the power supply and ground connections. A 3.3V source is connected to the device via a 4.7kΩ resistor. The device is connected to ground via a 4.7kΩ resistor. The power supply is labeled "NO REBOOT STARP" and "ENABLE: HIGH (INTERNAL WEAK PD)".

**Left Section (A-D):** Shows the BIOS debug port. The device is connected to a 3.3V source via a 4.7kΩ resistor. The power supply is labeled "BOOT STARP" and "ENABLE: LFC IS SELECT (INTERNAL WEAK PD)".

**Center Section:** Shows the main device and its connections. The device is connected to a 3.3V source via a 4.7kΩ resistor. The power supply is labeled "LPSS\_GSPH1 MOSI" and "LPSS\_GSPH0 MOSI".

**Right Section:** Shows the BIOS status table and the BIOS confirmation section. The table lists the status of various BIOS components (BOARD\_ID, BOARD\_ID2, BOARD\_ID3) and the BIOS confirmation section shows the connection of the BIOS debug port to the BIOS status table.

**Bottom Section:** Shows the BIOS confirmation section. The device is connected to a 3.3V source via a 4.7kΩ resistor. The power supply is labeled "BIOS CONFIRM" and "BIOS CONFIRM".

**Table:** A table showing the status of various BIOS components. The table has 4 columns: Status, BOARD\_ID, BOARD\_ID2, and BOARD\_ID3. The rows show the status of the components for different values of BOARD\_ID (0, 1, 2, 3).


**BIOS CONFIRM:** A section showing the connection of the BIOS debug port to the BIOS status table. The device is connected to a 3.3V source via a 4.7kΩ resistor. The power supply is labeled "BIOS CONFIRM" and "BIOS CONFIRM".

BOARD_ID_Status		BOARD_ID1		BOARD_ID2	
Status		R427	R428	R62	R66
0	L	0	1	L	0
1	L	0	1	H	1
2	H	1	0	L	0
3	H	1	0	H	1


Schematic Diagrams

M.2 (WLAN, 3G, SSD)

Sheet 23 of 48  
2 (WLAN, 3G, SSD)




## Audio Codec

Sheet 24 of 48  
Audio Codec


**PS8330B**

Sheet 25 of 48  
PS8330B




## AR\_TBT B - 27

## B.Schematic Diagrams




\_\_\_\_\_

# AR\_Power



## Schematic Diagrams

# ASM1543




**Sheet 28 of 48**  
**ASM1543**

## B.Schematic Diagrams




# TPS65982




Sheet 29 of 48  
TPS65982

**Sheet 30 of 48**  
**Type C**



USB




Sheet 31 of 48  
USB

[illegible]

HDD, ODD, LED B - 33

## CCD, MIC, LID, I/O Connector

**Sheet 33 of 48**  
**CCD, MIC, LID, I/O**  
**Connector**






Schematic Diagrams


5V, 5VS, 3.3V, 3.3VS, 3.3VA

Sheet 35 of 48  
5V, 5VS, 3.3V,  
3.3VS, 3.3VA







## VDD3, VDD5 B - 37



## DDR 1.2V/0.62VS, 2.5V


Sheet 37 of 48  
DDR 1.2V/0.62VS,  
2.5V






# VCORE, VCCGT Output Stage

Sheet 39 of 48  
VCORE, VCCGT  
Output Stage




# VCCSA




**VCCIO**

Sheet 41 of 48  
VCCIO




## 1.0DX\_VCCSTG/VCCSFR\_OC, 3.3VA



Sheet 42 of 48  
1.0DX\_VCCSTG/  
VCCSFR\_OC,  
3.3VA



Charger, AC-In




## Audio Board B - 45




Click Board

Sheet 45 of 48  
Click Board






Caddy Bay Board



B.Schematic Diagrams

Sheet 47 of 48  
Caddy Bay Board

## Power Seq.

Sheet 48 of 48  
Power Seq.



# Appendix C: Updating the FLASH ROM BIOS

## To update the FLASH ROM BIOS, you must:

- Download the BIOS update from the web site.
- Unzip the files onto a bootable CD/DVD/USB Flash Drive.
- Reboot your computer from an external CD/DVD/USB Flash Drive.
- Use the flash tools to update the flash BIOS using the commands indicated below.
- Restart the computer booting from the HDD and press **F2** at startup enter the BIOS.
- Load setup defaults from the BIOS and save the default settings and exit the BIOS to restart the computer.
- After rebooting the computer you may restart the computer again and make any required changes to the default BIOS settings.

## Download the BIOS

1. Go to [www.clevo.com.tw](http://www.clevo.com.tw) and point to **E-Services** and click **E-Channel**.
2. Use your user ID and password to access the appropriate download area (BIOS), and download the latest BIOS files (the BIOS file will be contained in a batch file that may be run directly once unzipped) for your computer model (see sidebar for important information on BIOS versions).

## Unzip the downloaded files to a bootable CD/DVD/ or USB Flash drive

1. Insert a bootable CD/DVD/USB flash drive into the CD/DVD drive/USB port of the computer containing the downloaded files.
2. Use a tool such as Winzip or Winrar to unzip all the BIOS files and refresh tools to your bootable CD/DVD/USB flash drive (you may need to create a bootable CD/DVD with the files using a 3rd party software).

## Set the computer to boot from the external drive

1. With the bootable CD/DVD/USB flash drive containing the BIOS files in your CD/DVD drive/USB port, restart the computer and press **F2** (in most cases) to enter the BIOS.
2. Use the arrow keys to highlight the **Boot** menu.
3. Use the “+” and “-” keys to move boot devices up and down the priority order.
4. Make sure that the CD/DVD drive/USB flash drive is set first in the boot priority of the BIOS.
5. Press **F4** to save any changes you have made and exit the BIOS to restart the computer.



### BIOS Version

Make sure you download the latest correct version of the BIOS appropriate for the computer model you are working on.

**You should only download BIOS versions that are V1.0X.XX or higher as appropriate for your computer model.**

Note that BIOS versions are not backward compatible and therefore **you may not downgrade your BIOS to an older version** after upgrading to a later version (e.g if you upgrade a BIOS to ver 1.0X.05, you **MAY NOT** then go back and flash the BIOS to ver 1.0X.04).



## BIOS Update

---

### Use the flash tools to update the BIOS

1. Make sure you are not loading any memory management programs such as HIMEM by holding the **F8** key as you see the message “**EFI Shell**”. You will then be prompted to give “**Y**” or “**N**” responses to the programs being loaded by EFI Shell. Choose “**N**” for any memory management programs.
2. You should now see **DISK fsX:\>** (X is the designated drive number for the CD/DVD drive/USB flash drive).
3. **Type the following command:**

**fsX:\> Flash.nsh**

4. The utility will then proceed to flash the BIOS.
5. You should then be prompted to press any key to restart the system or turn the power off, and then on again but make sure you remove the CD/DVD/USB flash drive from the CD/DVD drive/USB port before the computer restarts.

### Restart the computer (booting from the HDD)

1. With the CD/DVD/USB flash drive removed from the CD/DVD drive/USB port the computer should restart from the HDD.
2. Press **F2** as the computer restarts to enter the BIOS.
3. Use the arrow keys to highlight the **Exit** menu.
4. Select **Load Setup Defaults** (or press **F3**) and select “**Yes**” to confirm the selection.
5. Press **F4** to save any changes you have made and exit the BIOS to restart the computer.

### Your computer is now running normally with the updated BIOS

You may now enter the BIOS and make any changes you require to the default settings.