

Z50-HR(S204-SC) Schematics Document
Sandy Bridge
Intel PCH
2011-02-14
REV :-1

www.aitech1.ru

N12M GS2 HYN1GB

緯創資通

Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title

Cover Page

Size
A3

Document Number


Z50-HR { Huron River Platform}

Rev
-1

Date: Wednesday, March 02, 2011

Sheet 1 of 74

Z50-HR Block Diagram



Name	Schematics Notes
SPKR	Reboot option at power-up Default Mode: Internal weak Pull-down. No Reboot Mode with TCO Disabled: Connect to Vcc3_3 with 8.2-kΩ - 10-kΩ weak pull-up resistor.
INIT3_3V#	Weak internal pull-up. Leave as "No Connect".
GNT3#/GPIO55 GNT2#/GPIO53 GNT1#/GPIO51	GNT[3:0]# functionality is not available on Mobile. Mobile: Used as GPIO only Pull-up resistors are not required on these signals. If pull-ups are used, they should be tied to the Vcc3_3power rail.
SPI_MOSI	Enable Danbury: Connect to Vcc3_3 with 8.2-k? weak pull-up resistor. Disable Danbury: Left floating, no pull-down required.
NV_ALE	Enable Danbury: Connect to +NVRAM_VCCQ with 8.2-kohm weak pull-up resistor [CRB has it pulled up with 1-kohm no-stuff resistor] Disable Danbury: Leave floating (internal pull-down)
NC_CLE	DMI termination voltage. Weak internal pull-up. Do not pull low.
HAD_DOCK_EN# /GPIO[33]	Low (0) - Flash Descriptor Security will be overridden. Also, when this signals is sampled on the rising edge of PWROK then it will also disable Intel ME and its features. High (1) - Security measure defined in the Flash Descriptor will be enabled. Platform design should provide appropriate pull-up or pull-down depending on the desired settings. If a jumper option is used to tie this signal to GND as required by the functional strap, the signal should be pulled low through a weak pull-down in order to avoid asserting HDA_DOCK_EN# inadvertently. Note: CRB recommends 1-kohm pull-down for FD Override. There is an internal pull-up of 20 kohm for DA_DOCK_EN# which is only enabled at boot/reset for strapping functions.
HDA_SDO	Weak internal pull-down. Do not pull high. Sampled at rising edge of RSMRST#.
HDA_SYNC	Weak internal pull-down. Do not pull high. Sampled at rising edge of RSMRST#.
GPIO15	Low (1) - Intel ME Crypto Transport Layer Security (TLS) cipher suite with no confidentiality High (1) - Intel ME Crypto Transport Layer Security (TLS) cipher suite with confidentiality Note : This is an un-muxed signal. This signal has a weak internal pull-down of 20 kohm which is enabled when PWROK is low. Sampled at rising edge of RSMRST#. CRB has a 1-kohm pull-up on this signal to +3.3VA rail.
GPIO8	GPIO8 on PCH is the Integrated Clock Enable strap and is required to be pulled-down using a 1k +/- 5% resistor. When this signal is sampled high at the rising edge of RSMRST#, Integrated Clocking is enabled, When sampled low, Buffer Through Mode is enabled.
GPIO27	Default = Do not connect (floating) High(1) = Enables the internal VccVRM to have a clean supply for analog rails. No need to use on-board filter circuit. Low (0) = Disables the VccVRM. Need to use on-board filter circuits for analog rails.

PCIE Routing

LANE1	Mini Card1(WLAN)
LANE2	Card Reader
LANE3	N/A
LANE4	GIGA LAN
LANE5	N/A
LANE6	N/A
LANE7	N/A
LANE8	N/A

SATA Table

SATA	
Pair	Device
0	HDD1
1	N/A
2	N/A
3	N/A
4	ODD
5	N/A

USB Table

Pair	Device	
0	USB Ext. port 2	OC#0
1	USB Ext. port 1	OC#1
2	USB Ext. port 4	OC#2
3		
4	USB Ext. port 3	OC#3
5	X	
6	X	
7	X	
8	X	
9	CAMERA	OC#5
10	X	
11	X	
12	Mini Card1 (WLAN)	
13	BLUETOOTH	OC#7

Pin Name	Strap Description	Configuration (Default value for each bit is 1 unless specified otherwise)	Default Value
CFG[2]	PCI-Express Static Lane Reversal	1: Normal Operation. 0: Lane Numbers Reversed 15 -> 0, 14 -> 1, ...	1
CFG[4]		Disabled - No Physical Display Port attached to 1: Embedded DisplayPort. Enabled - An external Display Port device is 0: connectd to the EMBEDDED display Port	0
CFG[6:5]	PCI-Express Port Bifurcation Straps	11 : x16 - Device 1 functions 1 and 2 disabled 10 : x8, x8 - Device 1 function 1 enabled ; function 2 disabled 01 : Reserved - (Device 1 function 1 disabled ; function 2 enabled) 00 : x8, x4, x4 - Device 1 functions 1 and 2 enabled	11
CFG[7]	PEG DEFER TRAINING	1: PEG Train immediately following xxRESETB de assertion 0: PEG Wait for BIOS for training	1

www.aitech1.ru



N12M GS2 HYN1GB

緯創資通		Wistron Corporation	
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih, Taipei Hsien 221, Taiwan, R.O.C.			
Title			
Table of Content			
Size A3	Document Number	Rev	
	Z50-HR { Huron River Platform}	-1	
Date: Wednesday, March 02, 2011	Sheet 3	of	74


SSID = CPU

Note:
Intel DMI supports both Lane Reversal and polarity inversion but only at PCH side. This is enabled via a soft strap.

Note:
Intel FDI supports both Lane Reversal and polarity inversion but only at PCH side. This is enabled via a soft strap.
Lane reversal does not apply to FDI sideband signals.




Port	Strap	Enable	Disable
eDP	CFG[4]	Pull down to GND through a 1K ± 5% resistor	No Connect
	EDP_HDP	Pull down to GND through a 1K ± 5% resistor	Pull high to CPU VCCIO through a 10K ± 5% resistor



Signal Routing Guideline:
PEG_ICOMPO keep W/S=12/15 mils and routing length less than 500 mils.
PEG_ICOMPI & PEG_RCOMPO keep W/S=4/15 mils and routing length less than 500 mils.

SSID = CPU



N12M GS2 HYN1GB




緯創資通 **Wistron Corporation**
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title			
CPU (DDR)			
Size A3	Document Number		Rev
	Z50-HR { Huron River Platform}		-1
Date:	Wednesday, March 02, 2011	Sheet 6 of 74	





PEG DEFER TRAINING	
CFG7	1: PEG Train immediately following xxRESETB de assertion 0: PEG Wait for BIOS for training

SSID = CPU



No-stuff sites outside the socket may be removed.
No-stuff sites inside the socket cavity need to remain.




N12M GS2 HYN1GB




緯創資通 **Wistron Corporation**
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title			
CPU (VCC CORE)			
Size	Document Number	Rev	
Custom	Z50-HR { Huron River Platform }	-1	
Date:	Wednesday, March 02, 2011	Sheet	8 of 74

SSID = CPU




Disabling Guidelines for External Graphics Designs:
Can connect to GND if motherboard only supports external graphics and if GFX VR is not stuffed.
Can be left floating (Gfx VR keeps VAXG rail from floating) if the VR is stuffed





Refer to the latest Huron River Mainstream PDG (Doc# 436735) for more details on S3 power reduction implementation.



+V SM VREF CNT should have 10 mil trace width



Routing Guideline:
Power from DDR_VREF_S3 and +V_SM_VREF_CNT
should have 10 mils trace width.



VCCSA Output Decoupling Recommendation:
 1 x 330 uF
 2 x 10 uF at Bottom Socket Cavity
 1 x 10 uF at Bottom Socket Edge



H_FC_C22 1 TP901 Do Not Stuff


VCCSA_SENSE TP902 Do Not Stuff

N12M GS2 HYN1GB

緯創資通 **Wistron Corporation**
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title			
CPU (VCC GFXCORE)			
Size A3	Document Number		Rev
	Z50-HR { Huron River Platform}		-1
Date:	Wednesday, March 02, 2011	Sheet 9 of	74

SSID = CPU




N12M GS2 HYN1GB

緯創資通 Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title			
CPU (VSS)			
Size	Document Number	Rev	
A3	Z50-HR { Huron River Platform}	-1	
Date:	Wednesday, March 02, 2011	Sheet	10 of 74

SSID = MEMORY

PART NUMBER	Height	TYPE
62.10017.Q31	9.2mm	STANDARD
62.10017.N11	9.2mm	REVERSED




N12M GS2 HYN1GB

緯創資通 **Wistron Corporation**
21F, 88, Sec. 1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.








Title			DDR3-SODIMM2
Size	Document Number	Rev	
Custom	Z50-HR (Huron River Platform)	-1	
Date:	Wednesday, March 02, 2011	Sheet	12 of 74

CHANGE TO 71.0HM65.00U




PORT	DDI PCH Pin Names	SDVO Mapping	Display Port Mapping	HDMI/DVI Mapping
PORT-B	DDPB_[0]P	SDVO_RED	DDPB_[0]P	TMDSB_DATA2
	DDPB_[0]N	SDVO_RED#	DDPB_[0]N	TMDSB_DATA2#
	DDPB_[1]P	SDVO_GREEN	DDPB_[1]P	TMDSB_DATA1
	DDPB_[1]N	SDVO_GREEN#	DDPB_[1]N	TMDSB_DATA1#
	DDPB_[2]P	SDVO_BLUE	DDPB_[2]P	TMDSB_DATA0
	DDPB_[2]N	SDVO_BLUE#	DDPB_[2]N	TMDSB_DATA0#
	DDPB_[3]P	SDVO_CLK	DDPB_[3]P	TMDSB_CLK
	DDPB_[3]N	SDVO_CLK#	DDPB_[3]N	TMDSB_CLK#
	DDPB_AUXP	NA	DDPB_AUXP	NA
	DDPB_AUXN	NA	DDPB_AUXN	NA
	DDPB_HPD	NA	DDPB_HPD	HDMIB_HPD
	SDVO_CTRLCLK	SDVO_CTRLCLK	NA	HDMIB_CTRLCLK
	SDVO_CTRLDATA	SDVO_CTRLDATA	NA	HDMIB_CTRLDATA

SSID = PCH



USB Table

Pair	Device
0	USB Ext. port 4 OC#0
1	USB Ext. port 1 OC#1
2	USB Ext. port 2 OC#2
3	
4	USB Ext. port 3 OC#3
5	X
6	X
7	X
8	X
9	CAMERA OC#5
10	X
11	X
12	Mini Card1 (WMAX)
13	BLUETOOTH OC#7



A16 swap override Strap/Top-Block
Swap Override jumper

```
PCI_GNT#3    Low = A16 swap
              override/Top-Block
              Swap Override enabled
              High = Default
```

KBC CLK EM

USB 2.0 Overcurrent Pin Default Usage

Pin	Default Port Mapping	Pin	Default Port Mapping
OC0#	Port 0, Port 1	OC4#	Port 8, Port 9
OC1#	Port 2, Port 3	OC5#	Port 10, Port 11
OC2#	Port 4, Port 5	OC6#	Port 12, Port 13
OC3#	Port 6, Port 7	OC7#	Not Used

N12M GS2 HYN1GB


緯創資通 **Wistron Corporation**
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title	PCH (PCI/USB/NVRAM)
-------	----------------------------

Size A3	Document Number Z50-HR { Huron River Platform}	Rev -1
Date: Wednesday, March 02, 2011	Sheet 14 of 74	


SSID = PCH

Signal Routing Guideline:
DMI_ZCOMP keep W=4 mils and routing length less than 500 mils.
DMI_IRCOMP keep W=4 mils and routing length less than 500 mils.





For platforms not supporting Deep S4/S5

- 1.VccSUS3_3 and VccDSW3_3 will rise at the same time (connected on board)
- 2.DPWROK and RSMRST# will rise at the same time (connected on board)
- 3.SLP_SUS# and SUSACK# are left as 'no connect'
- 4.SUSWARN# used as SUSPWRDNACK/GPIO30



Deep S4/S5 Supported

Deep S4/S5 **Not** Supported




N12M GS2 HYN1GB

緯創資通 **Wistron Corporation**
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title	<i>PCH (DM I/FDI/PM)</i>
-------	---------------------------------

Size A3	Document Number Z50-HR { Huron River Platform}	Rev -1
Date: Wednesday, March 02, 2011	Sheet 15 of 74	

SSID = PCH



Integrated Clock Chip Enable	
HIGH (R2211 DY)- DISABLED [DEFAULT]	
ICC_EN#	LOW (R2211)- ENABLED

GPIO8 has a weak[20K] internal pull up.
Integrated Clock Enable functionality is achieved via soft-strap. The default is integrated clock enable.

DY 1 R2205
Do Not Stuff

PCH_GPIO27

【CKLIST P.66】

Deep Sleep	
GPIO27	HIGH (R2019 DY)- ENABLED [DEFAULT] LOW (R2019) - DISABLED




GPIO27 has a weak[20K] internal pull up.
If not used then use 8.2-kΩ to 10-kΩ pull-down to GND.

DY 1 R2212
Do Not Stuff


PLL_ODVR_EN

The On-Die PLL voltage regulator

NOTE:This signal has a weak internal pull-up 20K
ENABLED -- HIGH (R2212 UNSTUFFED) DEFAULT
DISABLED -- LOW (R2212 STUFFED)
If not used, 8.2-kΩ to 10-kΩ pull-up to +V3.3A power-rail.




Integrated Clock Enable functionality is achieved via soft-strap. The default is integrated clock enable.
This signal has a weak internal pull-down.
NOTE: The internal pull-down is disabled after PLTRST# deasserts.
NOTE: This signal should not be pulled high when strap is sampled.





SSID = PCH

Note:
For PCH debug with XDP, need to NO STUFF R2218




23 PCH_TEMP_ALERT# <<<
16 PCH_GPIO57 >>> PCH_GPIO57
If not used, 8.2 to 10-kΩ pull-up to VccSus3.3 (+V3.3A) OR pull-down to GND




NCTF TEST PIN:
A4, A44, A45, A46, A5, A6, B3, B47, BE1, BE49, BF1, BF49, B32, B349, BH3, BH47, B74, B744, B745, B746, B75, B76, C3, C48, D1, D49, E1, E49, F1, F49

COUGAR-GP-U2-NF



This signal has a weak internal pull-down.
NOTE: The internal pull-down is disabled after PLTRST# deasserts.
NOTE: This signal should not be pulled high when strap is sampled.



[VRAM_SIZE1:VRAM_SIZE2]
LL=512M / HL=1G / LH=2G



This signal has a weak internal pull-up.
Note: The internal pull-up is disabled after PLTRST# deasserts.
NOTE: This signal should not be pulled low. Leave as "No Connect".

TS Signal Disable Guideline:
TS_VSS1, TS_VSS2, TS_VSS3 and TS_VSS4 should not float on the motherboard. They should be tied to GND directly.

Core power : 3D3V_S0
Core power : 3D3V_S0




FDI TERMINATION VOLTAGE OVERRIDE	
GPIO37 (FDI_OVRVLTG)	LOW - Tx, Rx terminated to same voltage (DC Coupling Model DEFAULT)

W12M GS2 HYN1GB
緯創資通 Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih, Taipei Hsien 221, Taiwan, R.O.C.

Title	
PCH (GPIO/CPU)	
Size A3	Document Number Z50-HR { Huron River Platform}
Date: Wednesday, March 02, 2011	Sheet 18 of 74

SSID = PCH 6A




N12M GS2 HYN1GB

緯創資通 **Wistron Corporation**
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title			
PCH (POWER1)			
Size A3	Document Number		Rev
	Z50-HR { Huron River Platform }		-1
Date:	Wednesday, March 02, 2011		Sheet 19 of 74



SSID = PCH



緯創資通 **Wistron Corporation**
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title			
PCH (POWER2)			
Size A3	Document Number		Rev
	Z50-HR { Huron River Platform}		-1
Date:	Wednesday, March 02, 2011	Sheet 20 of	74


SSID = PCH



N12M GS2 HYN1GB

緯創資通		Wistron Corporation	
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih, Taipei Hsien 221, Taiwan, R.O.C.			
Title			
PCH (VSS)			
Size	Document Number	Rev	
A3	Z50-HR { Huron River Platform}	-1	
Date:	Wednesday, March 02, 2011	Sheet	21 of 74


SSID = KBC



EC GPIO standard PH/PL


PCB VERSION A/D(PIN#)	PULL-LOW RESISTOR	PULL-HIGH RESISTOR	VOLTAGE
SA	100.0K	10.0K	3.0V
SB	100.0K	20.0K	2.75V
SC	100.0K	33.0K	2.48V
-1	100.0K	47.0K	2.24V
Reserved	100.0K	64.9K	2.0V
Reserved	100.0K	76.8	1.87V
Reserved	100.0K	100.0K	1.65V


緯創資通 Wistron Corporation
 21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
 Taipei Hsien 221, Taiwan, R.O.C.








ADJ Table (Reference to SYNTON-TECH Metal Film Resistor E-96 $\pm 1\%$ Series)

RADJ1 (KΩ)	RADJ2 (KΩ)	VADJ (v)	OTZ Threshold Temperature (°C)
124	226	2.13	101
118	226	2.17	96.3
113	226	2.20	92.1
110	226	2.22	89.6
107	226	2.24	87
105	226	2.25	85.3
100	226	2.29	80.9









N12M GS2 HYN1GB

緯創資通 Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.


Title: **RTS5209 (CARD READER)**
Size: A3 Document Number: **Z50-HR { Huron River Platform}** Rev: -1
Date: Wednesday, March 02, 2011 Sheet 27 of 74

[illegible]

Power Sequence

EVT
DEL U3608


1 R3604 2 >>> ALL_SYS_PWROK 23.64
Do Not Stuff <<< PWR_VCCSA_PWRGD 15.35.41



www.aitech1.ru


Run Power

PVT




S3 Power

PVT



DVT




N12M GS2 HYN1GB

緯創資通 Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Power Plane Enable			
Size A3	Document Number	Rev	
Z50-HR (Huron River Platform)		-1	
Date: Wednesday, March 02, 2011	Sheet 29	of 74	

Adaptor in to generate DCBATOUT



N12M GS2 HYN1GB

緯創資通 **Wistron Corporation**
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title

DCIN JACK

Size
A4

Document Number


Z50-HR { Huron River Platform}

Rev
-1

Date: Wednesday, March 02, 2011

Sheet 31 of 74

BATTERY IDENTIFY



N12M GS2 HYN1GB

緯創資通 **Wistron Corporation**
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title

BATT CONN

Size
A3

Document Number

Z50-HR { Huron River Platform}



Date _____

Wednesday, March 02, 2011

Sheet	32
-------	----

Rev
-1




















	-1
34	



N12M GS2 HYW1G8

緯創資通 Wistron Corporation
21F, 88, Sec. 1, Hsin Tai Wu Rd., Neihu,
Taipei Hsien 221, Taiwan, R.O.C.

File: CHARGER BQ24725
Size: Document Number
A2: Z50-HR (Huron River Platform)
Date: Wednesday, March 02, 2011 Sheet 33 of 74



www.aitech1.ru

TONSEL	CH1	CH2
GND	200kHz	250kHz
VREF	300kHz	375kHz
VREG3 or VREG5	400kHz	500kHz

SKIPSEL	VREG3 or VREG5	VREF (2V)	GND
Operating Mode	OOA Auto Skip	Auto Skip	PWM only


N12M GS2 HYN1GB

緯創資通 Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsinchi, Taipei Hsien 221, Taiwan, R.O.C.


Title: **5V/3D3V(RT8223MGQW-GP-U1)**

Size A3 Document Number: **Z50-HR {Huron River Platform}** Rev: **-1**


Date: Wednesday, March 02, 2011 Sheet: 34 of 74



TPS51218D for 1D05V





79.47612.3FL
OSCON
Lelon 47uF, 25V
ESR<440mΩ, Iripple=230mA



Freq=360KHz


$$V_{out} = 0.704 * (1 + R1/R2)$$




20101114
Iomax=14A
OCP>21A

79.33719.L01
Panasonic cap 330uF
2V, ESR=9mohm


```
SSID = PWR.Plane.Regulator_1p5v0p75v
```



79.47612.3FL
OSCON
Lelon 47uF, 25V
ESR<440mΩ, Iripple=230mA



Close to pin23




Close to pin23


Iomax=1A
OCP>1.5A

Close to output cap pin1, not inside of the output cap


+0.75VS
I_{omax}: 1.2A



RT8207 for 1D5V and 0D75V



Close to PIN9




Mag. 1.0uH 10*10*4
DCR=2.9~3.3mohm
Idc=18A, Isat=36A

$I_{\text{omax}}=12\text{A}$


OCP>20A PVT

79.33719.L01
Panasonic cap 330uF
2V, ESR=9mohm



SSID = PWR.Plane.Regulator_1p8v

RT9025 for 1D8V_S0




N12M GS2 HYN1GB

緯創資通 Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title			LDO 1D8V(RT9025)	
Size	Document Number	Z50-HR { Huron River Platform}		Rev
A3				-1
Date:	Wednesday, March 02, 2011	Sheet	40	of 74

APL5916 for VCCSA



VCCSA_SEL	VCCSA_PWR
L	0.9V
H	0.8V


N12M GS2 HYN1GB

緯創資通 Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title LDO VCCSA(APL5916)
Size A3 Document Number 750-HR {Huron River Platform} Rev -1
Date: Wednesday, March 02, 2011 Sheet 41 of 74

SSID = VIDEO

LVDS CONNECTOR



N12M GS2 HYN1GB

緯創資通

Wistron Corporation



21F, 8B, Sec.1, Hsin Tai Wu Rd., Hsichin,
Taipei Hsien 221, Taiwan, R.O.C.

LCD Connector			
File	Document Number	Rev	
A2	Z50-HR (Huron River Platform)	-1	
Date:	Wednesday, March 02, 2011	Sheet	42 of 74

For EMI request

Close to CRT connector

The diagram illustrates the placement of EMI suppression components for three CRT connector signals: CRT_DDCCDATA_CON, CRT_HSYNC_CON, and CRT_DDCCCLK_CON. Each signal line is connected to a common ground plane through a series of components: a 100pF capacitor (C5008, C5009, C5010), a ferrite bead (DY), and a 100pF capacitor (C5011). The ground plane is labeled 'Do Not Stuff' in three locations, indicating where components should not be placed. The components are placed close to the CRT connector.



SSID = VIDEO








HDMI Level Shifter& CONNECTOR

13 HDMI_DATA2_C >>> C5119 1 >>> UMA Do Not Stuff HDMI_DATA2_R
13 HDMI_DATA2_C# >>> C5120 1 >>> UMA Do Not Stuff HDMI_DATA2_R#
13 HDMI_DATA1_C >>> C5121 1 >>> UMA Do Not Stuff HDMI_DATA1_R
13 HDMI_DATA1_C# >>> C5122 1 >>> UMA Do Not Stuff HDMI_DATA1_R#
13 HDMI_DATA0_C >>> C5123 1 >>> UMA Do Not Stuff HDMI_DATA0_R
13 HDMI_DATA0_C# >>> C5124 1 >>> UMA Do Not Stuff HDMI_DATA0_R#
13 HDMI_CLK_C >>> C5125 1 >>> UMA Do Not Stuff HDMI_CLK_R
13 HDMI_CLK_C# >>> C5126 1 >>> UMA Do Not Stuff HDMI_CLK_R#

61 HDMI_CLK# >>> HDMI_CLK# C5127 1 >>> 8CD1U10V2KX-5GP DIS
61 HDMI_CLK >>> HDMI_CLK C5128 1 >>> 8CD1U10V2KX-5GP DIS
61 HDMI_DATA0# >>> HDMI_DATA0# C5129 1 >>> 8CD1U10V2KX-5GP DIS
61 HDMI_DATA0 >>> HDMI_DATA0 C5130 1 >>> 8CD1U10V2KX-5GP DIS
61 HDMI_DATA1# >>> HDMI_DATA1# C5131 1 >>> 8CD1U10V2KX-5GP DIS
61 HDMI_DATA1 >>> HDMI_DATA1 C5132 1 >>> 8CD1U10V2KX-5GP DIS
61 HDMI_DATA2# >>> HDMI_DATA2# C5133 1 >>> 8CD1U10V2KX-5GP DIS
61 HDMI_DATA2 >>> HDMI_DATA2 C5134 1 >>> 8CD1U10V2KX-5GP DIS


RN5103,RN5104
For Intel SPEC the resistor need stuff 680 ohm
For VGA SPEC the resistor need stuff 499 ohm

DIS HDMI Detect



SSID = SATA


SATA HDD Connector



2ND = 20.81599.022


PVT

Delay HDD power



ODD Connector

SATA_RX- and SATA_RX+ Trace
Length match within 20 mil



22.10300.C41



2nd = 22.10300.D11

PVT


N12M GS2 HYN1GB

緯創資通		Wistron Corporation	
		21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih, Taipei Hsien 221, Taiwan, R.O.C.	
Title			
HDD/ODD			
Size	Document Number	Rev	
A3	Z50-HR { Huron River Platform}	-1	
Date:	Wednesday, March 02, 2011	Sheet	45 of 74


SSID = LOM



Close to LAN AR8151




EMI




N12M GS2 HYN1GB

SSID = Flash.ROM





SYSTEM SPI ROM
Socket : 62.10089.001



SPI ROM Equal length need to less than 500mil

PCH and EC length less than 6.5 inch




PVT

N12M GS2 HYN1GB

緯創資通 Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title **Flash(KBC+PCH)/RTC CONN**

Size A3 Document Number **Z50-HR { Huron River Platform}** Rev **-1**
Date: Wednesday, March 02, 2011 Sheet 48 of 74



N12M GS2 HYN1GB

緯創資通 **Wistron Corporation**
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title

USB Power SW

Size
A4

Document Number

Z50-HR { Huron River Platform}


Rev
-1

Date: Wednesday, March 02, 2011

Sheet 49 of 74

SSID = User.Interface
Bluetooth Module conn.

Bluetooth



N12M GS2 HYN1GB

緯創資通

Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title

Bluetooth

Size
A4

Document Number

250-HR { Huron River Platform}






Rev
-1

Date: Wednesday, March 02, 2011

Sheet 50 of 74

SSID = Wireless

Mini Card Connector(802.11a/b/g/n)




N12M GS2 HYN1GB





緯創資通 Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title: MINICARD(WLAN&WMAX)
Size: A3 Document Number: Z50-HR { Huron River Platform}
Date: Wednesday, March 02, 2011 Sheet 51 of 74
Rev: -1


Power button LED
Power STDBY_LED



WLAN_LED





Battery LED1(CHARGE)





Common wireless SW(mechanical)								
ON								
WLAN SW(software)	ON	OFF	ON	OFF	ON	OFF	ON	OFF
WWAN SW(software)	ON	ON	OFF	OFF	ON	ON	OFF	OFF
Bluetooth SW(software)	ON	ON	ON	OFF	OFF	OFF	OFF	OFF
LED	TURN ON							OFF

active	High	Low
WWAN(W_DISABLE#)	ON	OFF
WLAN(WLAN_LED#)	OFF	ON
Bluetooth(BT_LED)	ON	OFF






SSID = KBC

Internal KeyBoard Connector




TOUCH PAD



N12M GS2 HYN1GB

緯創資通 Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.



N12M GS2 HYN1GB

緯創資通

Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title

Hall Sensor

Size
A4

Document Number


Z50-HR { Huron River Platform}

Rev
-1

Date: Wednesday, March 02, 2011

Sheet 54 of 74

EVT



N12M GS2 HYN1GB

緯創資通

Wistron Corporation

21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title

Dubug connector

Size
A

Document Number

Z50-HR { Huron River Platform}



Rev

-1

Date: Wednesday, March 02, 2011



Sheet 55 of 74

SD/MS Card Reader



MS CONN.

www.aitech1.ru



SD CARD CONN.

N12M GS2 HYN1GB

緯創資通

Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.

Title	Author	Year	Journal	Volume	Page
...

CARD Reader CONN

Size


Document Number

Z50-HR { Huron River Platform}

Rev


Date: Wednesday, March 02, 2011

Sheet 56 of 74




N12M GS2 HYH1G8


USB BTB CONN



EVT



LED BTB CONN




www.aitech1.ru









N12M GS2 HYN1GB

緯創資通 Wistron Corporation
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih,
Taipei Hsien 221, Taiwan, R.O.C.


Title		
IO Board Connector		
Size	Document Number	Rev
A3	Z50-HR { Huron River Platform }	-1
Date: Wednesday, March 02, 2011	Sheet 59 of 74	





LVDS Interface








I2CA=>CRT, I2CC=>LVDS.



Missed 3x 0.1uF






www.aitech1.ru

FBCLK Termination place on VRAM side

```
|-----|
| DVT   |
| R8629 STRAP2_N12P-GV need 4.99K pull down |
| N12M-GS need 25K pull down                |
|-----|
```

N12P-GV->64.49915.6DL,N12M-GS->64.49915.6DL

```
STRAP2    PCI_DEVID{0}=1
          PCI_DEVID{1}=0
          PCI_DEVID{2}=0
          PCI_DEVID{3}=0
```



GPU_ROM_SI	for 1GBit	for 2GBit	for 1GBit	for 2GBit
	Hynix VRAM	Hynix VRAM	Samsung VRAM	Samsung VRAM
	RAM_CFG[0]=0	RAM_CFG[0]=0	RAM_CFG[0]=1	RAM_CFG[0]=1
	RAM_CFG[1]=1	RAM_CFG[1]=1	RAM_CFG[1]=1	RAM_CFG[1]=1
	RAM_CFG[2]=0	RAM_CFG[2]=1	RAM_CFG[2]=0	RAM_CFG[2]=1
	RAM_CFG[3]=0	RAM_CFG[3]=0	RAM_CFG[3]=0	RAM_CFG[3]=0

GPU_ROM_SO	VGA_DEVICE	=1 (low bit)
	SWR_ALT_ADDR	=0
	FB_0_BAR_SIZE	=0
	XCRL_417	=0 (High bit)

15K,1G>=35K

GPU_ROM_SCLK	PEX_PLI_EN_TERM	=0
	SLOT_CLK_CFG	=1
	SUB_VENDOR	=0
	PCI_DEVICEID[4]	=1


it's the last bit of p from 0x50P1

VIDEO MEMORY TABLE				
	HYNIX 128Mx16 0110	SAMSUNG 128Mx16 0111	HYNIX 64Mx16 0010	Samsung 64Mx16 0011
RO M_SIPD R8627	34.8Kohm 64.34825.6DL	45.3Kohm 64.45325.6DL	15Kohm 64.15025.6DL	20Kohm 64.20025.6DL



NVIDIA TABLE			
	N12P-Q1 ES DEV ID: 0x0DFE	N12P-Q1 QS DEV ID: 0x0DFA	N12P-Q3 DEV ID: 0x0DDA
ROM SIPD R8627	34.8Kohm 64.34825.6DL	15Kohm 64.15025.6DL	15Kohm 64.15025.6DL

Physical Strapping Pin	GPU Package	Power Rail	Logical Strapping Bit 3	Logical Strapping Bit 2	Logical Strapping Bit 1	Logical Strapping Bit 0
ROM_SCLK	GB1-64	VDD33	PCI_DEVIO[4]	SUB_VENDOR	SLOT_CLK_CFG	PEX_PLL_EN_TER M
	GB1b-64		PCI_DEVIO[4]	SUB_VENDOR	PCI_DEVID[5]	PEX_PMC_EN_TER M
ROM_SI	GB1-64	VDD33	RAM_CFG[3]	RAM_CFG[2]	RAM_CFG[0]	RAM_CFG[0]
	GB1b-64		RAM_CFG[3]	RAM_CFG[2]	RAM_CFG[1]	RAM_CFG[0]
ROM_SO	GB1-64	VDD33	YCLK_417	FB_0_BAR_SIZE	SMB_ALT_ADDR	VGA_DEVICE
	GB1b-64		FB1_17	FB_0_BAR	SMB_ALT_ADDR	VGA_DEVICE
STRAP0	GB1-64	VDD33	USER[3]	USER[2]	USER[1]	USER[0]
	GB1b-64		USER[3]	USER[2]	USER[1]	USER[0]
STRAP1	GB1-64	VDD33	3GIO_PAD_CFG_A DR[3]	3GIO_PAD_CFG_ADR [2]	3GIO_PAD_CFG_ADR [1]	3GIO_PAD_CFG_A DR[0]
	GB1b-64		3GIO_PAD_CFG_A [3]	3GIO_PAD_CFG_ADR [2]	3GIO_PAD_CFG_ADR [1]	3GIO_PAD_CFG_A DR[0]
STRAP2	GB1-64	VDD33	PCI_DEVIO[3]	PCI_DEVIO[2]	PCI_DEVIO[1]	PCI_DEVIO[0]
	GB1b-64		PCI_DEVIO[3]	PCI_DEVIO[2]	PCI_DEVIO[1]	PCI_DEVIO[0]
STRAP3	GB1-64	VDD33	SOR3_EXPOSED	SOR2_EXPOSED	SOR1_EXPOSED	SOR0_EXPOSED
	GB1b-64		SOR3_EXPOSED	SOR2_EXPOSED	SOR1_EXPOSED	SOR0_EXPOSED
STRAP4	GB1b-64	VDD33	RESERVED	RESERVED	PCIE_MAX_SPEED	DP_PLL_VDD33V

Mode	MULTI_STRAP_REF1_GND	MULTI_STRAP_REF0_GND	Strapping Resistor for other STRAP pins
Binary Production Strapping	40.2 k Ω , 1% to GND	NC	10 k Ω , 5%
Multi-level Strapping	40.2 k Ω , 1% to GND	40.2 k Ω , 1% to GND	Refer to section 12.1




 緯創資通		Wistron Corporation 21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih, Taipei Hsien 221, Taiwan, R.O.C.	
File			
GPU GPIO/MIC(4/5)			
Size	Document Number		Rev
Z50-HR (Huron River Platform)			-1
Date:	Wednesday, March 02, 2011	Sheet 53 of 74	



www.aitech1.ru


N12M GS2 HYN1GB

緯創資通		Wistron Corporation	
		21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih, Taipei Hsien 221, Taiwan, R.O.C.	
Title			
GPU GND(5/5)			
Size	Document Number	Rev	
A3	Z50-HR { Huron River Platform}	-1	
Date:	Wednesday, March 02, 2011	Sheet	64 of 74



VRAM


72.52G63.A0U







VRAM

72.52G63.A0U

72.41646.Q0U K4W1G1646G-BC11 Samsung 1Gb
 72.42164.D0U K4W2G1646C-HC11 Samsung 2Gb
 72.51G63.H0U H5TQ1G63DFR-11C Hynix 1Gb
 72.52G63.A0U H5TQ2G63BFR-11C Hynix 2Gb



N12M GS2 HYN1GB



72.41646.Q0U	K4W1G1646G-BC11	Samsung 1Gb
72.42164.D0U	K4W2G1646C-HC11	Samsung 2Gb
72.51G63.H0U	H5TQ1G63DFR-11C	Hynix 1Gb
72.52G63.A0U	H5TQ2G63BFR-11C	Hynix 2Gb

N12M GS2 HYN1GB

SSID = PWR.Plane.Regulator_GFX

$$V_{out} = 0.75V * (R1 + R2) / R2$$

Design Current = 20A
24.14A < OCP < 24A

N12M-GS2

P-State	PWR_VGA_CORE_D1	PWR_VGA_CORE_D0	VGA_CORE_PWR
P8 Hot	L	L	0.875V
P0 Hot, P8 Cold	L	H	1.0V
P0 Cold	H	L	1.025V

Memory clock: P0->800MHz, P8->405MHz

Engine clock: P0->573.5MHz, P8->270MHz

N12P-GV

P-State	PWR_VGA_CORE_D1	PWR_VGA_CORE_D0	VGA_CORE_PWR
P8 Hot	L	L	0.85V
P0 Hot, P8 Cold	L	H	1.0V
P0 Cold	H	L	1.025V

Memory clock: P0->800MHz, P8->405MHz

Engine clock: P0->740MHz, P8->270MHz

P0 Hot-> over 60 °C
P0 Cold-> under 60 °C

Switching freq->350KHz

Frequency setting
470K -->165KHz
200K -->323KHz
100K -->500KHz

I/P cap: 10U 25V K1206 X5R/ 78.10622.52L
Inductor: 1.5UH PCMC104T-1R5MN Cyntec DCR:4.2mohm Isat =33Arms 68.1R510.10J
O/P cap: 330U 2V EEFSX0D331ER 9mOhm 3Arms Panasonic/ 79.33719.L01
H/S: SI7686DP/ POWERPAK-8/11mOhm/14mOhm@4.5Vgs/ 84.07686.037
L/S: SI1460DP/ POWERPAK-8/ 4.9mOhm/6.1mohm@4.5Vgs/ 84.00460.037

RT8208A	RT8208B	G0	G1	G0	G1	Output Voltage Equation
0	0	1	1	1	1	$V_{out} = \frac{R1+R2}{R2} \times 0.75$
1	0	0	1	1	1	$V_{out} = \frac{R1+(R2/R3)}{(R2/R3)} \times 0.75$
0	1	1	0	1	1	$V_{out} = \frac{R1+(R2/R4)}{(R2/R4)} \times 0.75$
1	1	0	0	1	1	$V_{out} = \frac{R1+(R2/R3/R4)}{(R2/R3/R4)} \times 0.75$

N12M GS2 HYN1GB

緯創資通

Wistron Corporation

21F, 8B, Sec.1, Hsin Tai Wu Rd, Hsichu, Taipei Hsien 221, Taiwan, R.O.C.

Title

RT8208B +VGA CORE

Size

Document Number

Z50-HR { Huron River Platform} -1

Date













Wednesday, March 02, 2011

Sheet

67




of

74



Z15-HR POWER UP SEQUENCE DIAGRAM

DIS_ONLY POWER UP SEQUENCE



SYSPWROK
Active Sleep Well (ASM) Power OK: When asserted, indicates that power to the ASM sub-system is stable. (Vocakm[105C_VTT])

APWROK
Active Sleep Well (ASM) Power OK: When asserted, indicates that power to the ASM sub-system is stable. (Vocakm[105C_VTT])

PWR0K
Power OK: When asserted, PWR0K is an indication to the Cougar Point that all of its core power rails have been stable for 10 ms. PWR0K can be driven asynchronously. When PWR0K is negated, the Cougar Point asserts PLTRST#. NOTE: It is required that the power rails associated with PCI/PCIe typically the 3.3 V, 5 V, and 12 V core well rails have been valid for 99 ns prior to PWR0K assertion in order to comply with the 100 ns PCI 2.3/PCIe 1.1 specification on PLTRST# deassertion. PWR0K must not glitch, even if RESET# is low.

Platform Reset: The Cougar Point asserts PLTRST# to reset devices on the platform (e.g., SIO, FW, LAN, Processor, etc.). The Cougar Point asserts PLTRST# during power-up and when S/W initiates a hard reset sequence through the Reset Control register (I/O Register CP9h). The Cougar Point drives PLTRST# inactive a minimum of 1 ms after both PWR0K and SYS_PWR0K are driven high. The Cougar Point drives PLTRST# active a minimum of 1 ms when initiated through the Reset Control register (I/O Register CP9h). NOTE: PLTRST# is in the VccBus3_3 well.

N12M GS2 HYMNIGB

緯創資通 Wistron Corporation
21F, 88, Sec.1, Hsin-Tai Wu Rd., Hsinchu, Taiwan 300, R.O.C.

Power Sequence

Size Document Number Rev
A2 Z50-HR (Huron River Platform)
Date: Wednesday, March 02, 2011 Sheet 70 of 74

Reversion History

EVT

(2010/09/28)
P.5 CPU (THERMAL/CLOCK/PM)
P.7 CPU (RESERVED)
P.9 CPU (VCC_GFXCORE)
P.13 PCH (LVDS/CRT/DDI)
P.14 PCH (PCI/USB/NVRAM)
P.15 PCH (DM I/FDI/PM)
P.16 PCH (PCI-E/SMBUS/CLOCK/CL)
P.17 PCH (SPI/RTC/LPC/SATA/IHDA)
P.18 PCH (GPIO/CPU)
P.22 KBC_Reset
P.23 KBC Nuvoton NPCE795

DUMMY RN501 pull high 1D05V_VTT for intel bebug use
Delete R706~R709 for no M3 function
Delete R904,R905,R901 , because R902 has pull low
Delete LVBS B channel for Z70
Reserved EC1803 for EMI
1.DUMMY R1922 ,internal already pull high,2 Del R1925 for intel debug.
1.Delete RN2017 for no display port,2 R2005 dummy, R2004 mount for PEG_CLKREQ# need pull high
DEL R2115~R2120,for intel JTAG no use
Add PCH_GPIO22 for VRAM Frequency 800MHZ to 900MHZ
Add VEDS_VEVS_Thermal_System_Protection_Rev1.0.0
1.ADD GPIO:FAN_PROTECT_DISABLE#,
2.ADD MODEL_ID for Z40,Z50 model,
3.ADD R2757 for vendor suggest ,
4.R2724 CHANGE TO 20K for SB Ver.
5.ADD BT_PRS2# for BT present.

P.24 Thermal P2800

1.CHANGE FAN PIN DEFINE,2.MOUNT D2802 for Vbemf(back emf),
3.U2802~U2806 pin4 connector to pin5 pull high follow Thermal_System_Protection_Rev1.0.0

P.21 Audio Codec_CX20671-21Z
P.22 Atheros 8151
P.27 RTS5209 (CARD READER)
P.28 Audio DE-POP Circuit
P.29 Power Plane Enable
P.30 S3 reduction

CHANGE Codec to CX20671
CHANGE LAN to Atheros 8151
DUMMY R3202 for use external EEPROM
Add Q3301,R333 for CODEC multi-function
Change r3626 to 20k for 3D3V_S3 Leakage

P.32 BATT CONN
P.34 CPU Core-1(1SL95831)

1.Del R577 for double pull low,2.Change Q3708_G net to PM_SLP_S3# for Sequence
3.DUMMY R3724 mount Q3712,R3726,R3722,R3723,Q3707,C3706 for 0D75_EN timing.
1.ADD D3906 for battery Protection,2.MOUNT D3901~D3905 for EMI
1.ADD PR4231,PC4233,PR4236,PC4234,MOUNT PR4221,PR4222,PR4420 ,Intel spec update for feedback compensate.
2.mount PR4221,PR4222,PR4420,PR4233~PR4235 for sensor MOS temperature.

P.42 [LCD Connector]
P.42 [LCD Connector]
P.44 [HDMI Level Shifter/Conn]
P.45 [HDD/ODD]
P.46 [Audio Jack]
P.46 [Audio Jack]
P.47 [LAN Connector]
P.51 [MINICARD]
P.52 [LED Board/Power Button]
P.52 [LED Board/Power Button]
P.52 [LED Board/Power Button]
P.52 [Key Board/Touch Pad]
P.55 [Debug connector]
P.58 [UVP Protect]
P.58 [UVP Protect]
P.58 [UVP Protect]
P.59 [IO Board Connector]
P.59 [IO Board Connector]
P.59 [IO Board Connector]
P.59 [IO Board Connector]
P.61 [GPU HDMI/LVDS/CRT(2/5)]
P.61 [GPU HDMI/LVDS/CRT(2/5)]
P.63 [GPU_GPIO/MIC(4/5)]
P.63 [GPU_GPIO/MIC(4/5)]
P.67 [RT8208B_+VGA_CORE]
P.69 [UNUSED PARTS/EMI Capacitors]
P.69 [UNUSED PARTS/EMI Capacitors]

Change LCD1 to 30pin and pin define
Add TR4901 for EMI
F5101 change to 69.4R500.151 POLYSWITCH
Change R5601 to 147K for delay timing
Add SPKR1 small board move to MB
R5808 and R5809 change to 3.0K for Conexant FAE suggestion
XF1 change to 68.89246.301 common part
Add WLAN/BT COMBO function
1.PWRLED1 change to 83.00195.N70 for green color
Add WLAN/BT COMBO LED signal pin
Delete Q86 and Q85 for function board no PWR/STDBY LED
Add EC6905 and EC6906 for EMI
Add DB1 for SW debug
Change net from UL_AD_OFF_4 to UL_AD_OFF_41 net name wrong
RN67 separate to R7816 1Mohm and R7817 80Kohm for change shutdown voltage detect
Add C7801 10UF/25V for change shutdown voltage detect
USBCN2 change to 26pin for USB board add G709 thermal sensor
Add F8201, F8202 and F8203 POLYSWITCH for comtmr request
Add TR8201, TR8202 and TR8203 for EMI
PWRCN1 change to 10pin for function board no SPKR1 and PWR/STDBY LED
Add LDO 3D3V_VGA_S0_DACA power for INCREASE POWER
Mount R8402 BOM error because HDMI no display
R8630 change to 45K for N12P-GV Device ID 0x107F
R8627 change to 45K for Samsung VRAM 2Gbit size
Add PU9205 low-side mosfet for N12P-GV NVVDD 20.02A
Add TPSPR1 for EMI
Mount EC9740 for EMI

(2010/09/29)
P.15 PCH (DMI/FDI/PM)

Add U1901, D1901, D1902, C1901, R1929~R1931 for
RSMRST#. PWROK must be "Low" earlier than PCH power down.
D2603 change to 83.R5003.C8F
D6001 change to 83.BAS70.011 for customer request
Del R1401 for use DDR_VREF_S3 POWER
Del R1501 for use DDR_VREF_S3 POWER
Change D3801(TVS) for surge voltage

P.22 KBC_Reset
P.60 [RTC Connector]
P.11(DDR3-SODIMM1)
P.12 (DDR3-SODIMM2)
P.31 DCIN JACK

(2010/09/30)
P.29 Power Plane Enable
P.25 Audio Codec_CX20671-21Z
P.67 [RT8208B_+VGA_CORE]
P.68 [DISCRETE VGA POWER]

Add D3603 for protect FET AO4468
Add C2905, C2925 and R2923(DY), R2924(DY) for vendor request
PR9203 change to 10R, PR9208 change to 15K for VGA_CORE keep 0.9V
R9302 change to 20K for 1D05V_VTT enbale timing

(2010/10/01)
P.20 [PCH (POWER2)]
P.22 [KBC_Reset]
P.24 Thermal P8200
P.25 Audio Codec_CX20671-21Z
P.28 Audio DE-POP Circuit

D2401, D2402 change to 83.R2004.B8F for common part
Q2602 change to 84.02222.V11, Q2601 change to 84.C3906.A11 for common part
Q2801 change to 84.03904.X11 for common part
D2901, D2902 change to 83.R2004.B8F for common part
Q19 change to 84.C3906.A11, Q20 change to 84.03904.X11
Q18 change to 84.09114.A11, Q25 change to 84.C3906.A11 for common part
Q3707 change to 84.03904.X11, U3702 change to 73.01G09.0AB for common part
D3908 change to 83.00016.F11 for common part
U6001 change to 72.25320.C01 for common part
U6301 change to 74.07534.A7F, U6302 change to 73.01G08.EHG for common part
X8601 change to 82.30034.641 for common part

P.30 S3 reduction
P.32 BATT CONN
P.48 Flash(KBC+PCH)
P.50 BLUETOOTH
P.63 [GPU_GPIO/MIC(4/5)]

Mount R1920, GPIO pin need to Pull Hi for PCH GPIO multi-function
Add R3209~R3211,C3212~C3214 for customer request
D3604 change to schottky for customer request
PD4002 change to 83.10004.08M for common part
Change R6505 to 0805 size for meet PCIE MINI card max power spec
Mount R3704, Q3702 for Huron River S3 reduction Desing Guide

(2010/10/04)
P.15 PCH (DMI/FDI/PM)
P.27 RTS5209 (CARD READER)
P.29 Power Plane Enable
P.33 CHARGER BQ24725
P.51 [MINICARD]
P.30 S3 reduction

ADD corner test point for CPU
ADD corner test point for PCH
ADD PU4006,PR4017,PR4018,PQ4001
ADD PU4006,PR4017,PR4018,PQ4001
(Q56 pin D connect to AD+)
(R9316 pin 1 connect to AD+)
add R9320 and DUMMY it. (Part number 64.10045.6DL)
connect R9320 pin 1 to ACP_UVP.
change C568 to the part number 78.10620.51L
add C9322 component.(part number 78.10620.51L)
HDMI_CONN pin17 connect to GND
PR9208 change to 17.8k
P8603 change to 15k
R8617 DUMMY, R8625 PU 10K for vendor suggest

(2010/10/05)
P.7 CPU (RESERVED)
P.18 PCH (GPIO/CPU)
P.33 CHARGER BQ24725
P.57 [UVP Protect]
P.58 [UVP Protect]

P.44 [HDMI Level Shifter/Conn]
P.67 [RT8208B_+VGA_CORE]
P.63 [GPU_GPIO/MIC(4/5)]
P.63 [GPU_GPIO/MIC(4/5)]

(2010/10/07)
P.49 USB Power SW
P.17 PCH /P.24
P.44 [HDMI Level Shifter/Conn]

(2010/10/14)
P.18 PCH (GPIO/CPU)

Add F6101 POLYSWISH 2A for USB power
Change net name from "+3VS_+1.5VS_HDA_IO" to "+3VS_HDA_IO"
Del HDMI Level Shifter

R2204 BOM change to 390ohm for intel spec

N12M GS2 HYN1GB			
緯創資通		Wistron Corporation	
		21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih, Taipei Hsien 221, Taiwan, R.O.C.	
Title			
Change History			
Size	Document Number	Rev	
Custom	750-HR (Huron River Platform) -1		
Date:	Wednesday, March 02, 2011	Sheet	71 of 74

Reversion History

DVT

(2010/11/16-2010/11/17)

P17--C2101, C2102 change to 6pF
Reason: Crystal vendor suggestion (32.768K)
Possible Risk: Rework OK

P17--Add R2126 ~ R2130 and C2105-C2110.
Reason: Reserver for LPC debug by EC VEVs
Possible Risk:

P18--DUMMY R2204
Reason: For customer request THERMTRIP# Shutdown Policy
Possible Risk: Rework OK

P22--R2604 stuff to IMVP_PWRGD, Q2602 change to 2N7002
Reason: For customer request THERMTRIP# Shutdown Policy
Possible Risk: Rework OK

P23--BT_PRS# add R2729 pull-up to 3D3V_S5
Reason: The VEVs request BT_PRS# signal be high when Module is not present so we add it.
Possible Risk:We already rework to finish BT VEVs report.

P23-- R2724 change to 33K
Reason: For SC version
Possible Risk:

P23--PCH_SML1_CLK,PCH_SML1_DATA Change power source to 3D3V_S5
Reason: If PH 3D3V_AUX_S5. When DC mode will cause leakage Problem
Possible Risk: Rework OK.

P24-- Add C2803=0.1uF
Reason: 5V has drop when fan power on so add a cap for soft start
Possible Risk: Rework OK.

P25--Stuff EC2901,EC2902
Reason:FOR EMI request
Possible Risk:

P25--DUMMY R2919 ,stuff R2922
Reason: "codec verb table" set mute functio is high active so we change it..
Possible Risk: Rework OK.

P26--DUMMY Q3101 R3104,R3110,ADD R3112,R3111
Reason:LAN_CLK_REQ# and PCIE_WAKE# no leakage on S3.
Possible Risk: Rework OK.

P26--Change C3126, C3127 to 18pF
Reason: Crystal vendor suggestion (25MHz for LAN)
Possible Risk: Rework OK.

P27--Dummy U3202, mount R3202
Reason: Use card reader IC internal EFUSE
Possible Risk: Rework OK

P29--R3626 change to 0ohm
Reason:First we use resistor to do voltage divider for protecting U3601 (let gate voltage < spec) but it is not safty so we add Zener diode D3603 to protect U3601.So Voltage divider do not need.
Possible Risk: Rework OK.

P29--Add Q3606, R3608 (DY)
Reason: Reserve 3D3V_S3 discharge circuit
Possible Risk: Rework OK

P30--DUMMY R3714,Q3704
Reason:When enter S3, DDR_VREF_S3 still have power. So it cannot do discharge when enter S3.
Possible Risk:

P30--DUMMY R3727,Q3713 ,replace PM_SLP_S3 net by PS_S3CNTRL .
Reason:PS_S3CNTRL control S3 discharge can instead of R3612,Q3603
Possible Risk:

P30--R3722 change to 10k,R3723 change to 3.3k,C3706 change to 4.7kohm, stuff C3707.
Reason:for S3 resume issue and sequence timing(ID 0547)
Possible Risk:Rework OK.

P32--add EC3901.EC3907,EC3908,EC3909
Reason:for EMI request
Possible Risk:

P43--R5001, R5002, RN5003 change to 4.7K for DIS SKU
R5001, R5002=2.7K, RN5003=2.2K for UMA SKU
Reason: For CRT DDC signal VEVs report
Possible Risk: Rework OK

P44-- R5133,R5134 change 3.3K for UMA sku, 4.7K for DIS SKU
Reason: For HDMI DDC signal VEVs report
Possible Risk: Rework OK

P45--R5601 change to 100k,R5603 change to 220k,C5614,C5604 change to 1u
Reason:for delay HDD power off timing
Possible Risk:Rework OK

P46--R5805,R5806,R5807,R5810,R5811,R5812 change to 11ohm.
Reason:For VEVs audio full scale output vottage(FSOV) report
Possible Risk:Rework OK.

P46--Add EC5804,EC5805,EC5806,EC5807,ED5808,ED5809
Reason:for EMI request (ED is mean diode)
Possible Risk:

P49--Add TR6101
Reason:for EMI request
Possible Risk:Rework OK and USB eye diagram pass.

P56--Add SD DATA_CLK_CMD 47 ohm damping(RN7403,R7401,R7404)
Reason:For cardreader VEVs report overshoot and undershoot
Possible Risk: Rework OK.

P57--RTC_PWR change to RTC_AUX_S5 power
Reason: Unplug AC will auto shut down after Remove RTC battery
Possible Risk: Rework OK

P59--Change USB BD FFC CONN pin define
Reason:del G709 on USB BD then add one usb power and ground pin for USB voltage drop issue. (ID 0583)
Possible Risk:

P62--R8504, R8505 change to 162ohm
Reason: NV FAE suggestion
Possible Risk:

P63--Change GPU GPIO strap pin R8626 to 4.99K, R8619 to 10K, R8629 to 4.99K for N12P-GV, R8629 to 25K for N12M-GS2, Dummy R8630 Dummy R8632, mount R8633=35K
Reason: NV FAE suggestion for GPU HW strap pin
Possible Risk:

P63--R8607 change to 470ohm
Reason: Crystal vendor suggestion (27MHz)
Possible Risk:Rework OK

P63--R8639 change to15K ohm
Reason: Resolve ID 0617 no HDMI audio output
Possible Risk:Rework OK

P67--Change PR9206 to 49.9K; add PR9218,PQ9202 for VGA_CORE discharge circuit.
Reason:For GPU VEVs Sequence Issue (ID 01019)
Possible Risk: Rework ok.

P68--Change R9303 to 0ohm ,R9315 to 2.2K, C9309 to 1uF; Dummy C9304
Reason:For GPU VEVs Sequence Issue (ID 01019)
Possible Risk: Rework ok.

P69--add DCBATOUT and 1D5V_S3 POWER plane capacitance
Reason:For EMI request
Possible Risk:

(2010/11/22)

P18--Delete R2220, R2221
Reason: Only use 900MHz VRAM frequency
Possible Risk: Rework OK

P22--Add Q2610,Q2607,D2606,R2608,R2602,C2602
Reason: For UVP circuit Simplification and Verification by 3V_5V_EN
Possible Risk: Rework OK

P44--add C5103 0.1uF.
Reason: Resolve HDMI DDC/CEC Capacitance fail (Issue ID 1106)
Possible Risk: Rework OK

P69--Add SPR1
Reason: For EMI request
Possible Risk:

(2010/11/24)

P17--Add C2105,C2107 ~ C2110
Reason: Reserver for LPC debug by EC VEVs
Possible Risk:

P19--Add C2324,C2325,L2302,L2303,L2304
Reason: Improve DMI eye diagram
Possible Risk: Under Verify (ZM and ZG-I different)

P48--DelR6004,R6003 change to 1k
Reason: customer request do not need "RGT_PWR"net
Possible Risk: Rework OK

P60--PEX_SVDD_3V3 power rail from 1.05V change to 3.3V
Reason: NV FAE suggution for N12M-GS2/N12P-GV GPU
Possible Risk:

(2010/11/25)

P9--R906, R907 change to 10ohm
Reason: Customer requirement
Possible Risk:

P24-- Add F2801
Reason: 0.5A POLYSWITCH for FAN by Customer requirement
Possible Risk:

P35--Dummy PR4230, PR4250, PR4228, PR4229
Reason: Customer requirement
Possible Risk:

(2010/11/26)

P32--Change U3901 to R5G05000N753NF
Reason: Battery authentication IC package is shrunk and renamed as R5G05000N753NF.
Possible Risk:

(2010/11/29)

P58--dummy R9320
Reason: customer request
Possible Risk:

P58--R8629 change to 30k for N12M
Reason: N12M GPU change new device ID
Possible Risk:

N12M GS2 HYN1GB

緯創資通		Wistron Corporation	
		21F, 88, Sec. 1, Hsin Tai Wu Rd., Hsichih, Taipei Hsien 221, Taiwan, R.O.C.	
Title			
Change History			
Size Custom	Document Number		Rev
Z50-HR (Huron River Platform) -1			
Date:	Wednesday, March 02, 2011	Sheet 72 of	74

(POWER modify)

P8--R801, R802 change to 10ohm, reserve R804, R805=10ohm
Reason: Vendor suggation
Possible Risk:

P33--Add PR4019, PR4020
Reason: Vendor TI suggestion reserve
Possible Risk:

P33--PU4001, PU4002, PU4006 change to 84.02657.037
Reason: Low Rds(on), decrease consumption
Possible Risk:

P34--Change PU4101 PU4106 PU4104 PU4105
Reason: Material shortage issue
Possible Risk:

P34--PR4104 change to 95.3K, PR4103 change to 84.5K
Reason: OCP modify
Possible Risk:

P35--Change PR4205 to 2.26K, PR4227 to 3.74K
Reason: Load line
Possible Risk:

P35--Change PR4206 to 21.5K, PC4205 to 0.01uF, PR4218 to 36K
PC4207 to 0.01uF
Reason: Vendor Intersil suggestion for Imon=2.7V
Possible Risk:

P35--Dummy PC4224, PC4209
Reason: FAE suggestion for delay issue
Possible Risk:

P35--Change PR4239 to 1.69K
Reason: For Intel spec increase efficiency
Possible Risk:

P36--Delete PU4308, PU4311, PU4312, PU4314
change PL4303, PL4302 to 68.R3610.10X
Reason: Thermal issue, use low DCR
Possible Risk:

P36--Change PU4308~ PU4315
Reason: Material shortage issue
Possible Risk:

P37--Change PU4401 to 84.07698.037, PU4403 to 84.00308.B03
PL4401 to 68.R3610.10M
Reason: Material shortage issue
Possible Risk:

P37--Change PR4404 to 536ohm
Reason: OCP modify
Possible Risk:

P37--Change PC4405 TO 10K
Reason: Transient
Possible Risk:

P38--Change PR4504 to 93.1K
Reason: OCP modify
Possible Risk:

P38--Change PU4502 to 84.07698.037, PU4503 to 84.00312.037
Reason: Material shortage issue
Possible Risk:

P38--Change PL4501 to 68.R8810.10G
Reason: Increase ripple
Possible Risk:

P39--Change PR4603 to 32.4K
Reason: OCP modify
Possible Risk:

P39--Change PU4602 to 84.07698.037, PU4603 to 84.00312.037
Reason: Material shortage issue
Possible Risk:

P41--Add PG4810, PG4809
Reason: Increase input current
Possible Risk:

P67--Change PU9202, PU9304, PU9205 PL9201
Reason: Material shortage issue
Possible Risk:

P67--Mount PTC9203
Reason: Decrease output ripple
Possible Risk:

P58--Dummy D46
Reason: For UVP circuit by Customer requirement
Possible Risk:

P58--Add Q57
Reason: Prevent battery only, voltage through body diode return back
to adaptor, induce unknow risk
Possible Risk:

P67--Add PG9218~PG9220, PG9222~PG9224
Reason: Increase input current
Possible Risk:

P67--PR9208=13.3k, PR9210=78.7k, PR9209=78.7k, PR9213=66.5K for N12M-GS2
PR9208=10k, PR9210=75k, PR9209=49.9k, PR9213=42.2K for N12P-GV
Reason: Tune GPU P-State voltage
Possible Risk:

(ME Connector change)

1. Mini Card CONN: (MINI1)
Issue: The ANT cable's tube might
has risk to overlap with Low-case's shielding

Action: Changed the CONN height from 8.0 to 5.3mm

2. RTC & SPK & Fan CONN: (RTC1,SPKL1,SPKR1,FAN1)
Issue: Follow Sandra's request to
change the terminal with Gold plating

Action: change the CONN's terminal from Tin to Gold terminal

3. ODD & HDD CONN: (ODD1,HDD1)
Issue: Follow WKS's request to change
from SMT to DIP type for prevent Empty solder,
Floating solder Excess solder

Action: Changed the CONN from SMT to DIP type

4. TP Switch: (SWL1,SWR1)
Issue: Follow WKS's request to change
new Switch for prevent Empty solder,
Floating solder and Excess solder ect.

Action: Changed new switch.

5. WLA: (MINI1)
Issue: Issue: cost too high
Action: Changed size the same new connector.

N12M GS2 HYN1GB

緯創資通		Wistron Corporation	
21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih, Taipei Hsien 221, Taiwan, R.O.C.			
Title			
Change History			
Size	Document Number	Rev	
A3	750-HR (Huron River Platform)	-1	
Date:	Wednesday, March 02, 2011	Sheet	73 of 74

Reversion History

PVT

(2010/10/28~2011/01/05)

P63_ Dummy RN8606
Reason: for double pull high
Possible Risk: Rework ok

P30_ Delete R3714, Q3704(Q00008)
Reason:customer request delete S3 error circuit
Possible Risk: Rework ok

P32_change D3908 to Schottky diode(Q-00009)
Reason:customer request
Possible Risk: Rework ok

P58_UVP R9316 change to 475K
Reason: customer request
Possible Risk: Rework ok

(2011/01/11~01/18)

P8_Add R805,R804(Q00002)
Reason: customer request
Possible Risk: Rework ok

P15_G680 reset_change D1901 to schottky diode(Q00003)
Reason: customer request
Possible Risk: Rework ok

P15_ Delete R1928
Reason: Customer request for DeepSleep issue
Possible Risk: Rework ok

P20_ Delete R2415
Reason: Customer request for DeepSleep issue
Possible Risk: Rework ok

P22_ R2604 change to 10.5K, R2635 change to 8.87K, Q2602 change to transistor 84.02222.V11, R2612 change to 100K, Mount R2616
Dummy Q2607, R2602, C2602, Q2607, C2613, Q2606, R2606, R2615, C2612, Q2604, RN2605, Q2601, R2613, Q2603, Add R2619, Q2611, Q2612, D2605, R2611,R2617(Q00004)
Reason: Customer request
Possible Risk: Rework OK

P8, 9, 37_ Add ED801, ED802, ED901, ED902, ED4501, ED4502 Varistor
Reason: EMI request for ESD protect
Possible Risk: Rework OK

P24_ U2801 power plane change to 3D3V_AUX_S5
Dummy R2809, (Q-00035)
Reason: Customer request for Thermal Sensor P2800 Issue
Possible Risk: Rework OK

P24_ R2811&R2812 change to 29.4K, R2810 change to 44.2K
R2824 change to 33.2K, R2833 change to 36.5K(Q-00006)
Reason: Thermal request for G709 temperature protect
Possible Risk: Rework OK

P37_ Mount PR4510, PR4511,PC4510
Reason: Customer request for VCCIO sense function (Q00013)
Possible Risk: Rework OK

P42_ Change LCD1 connector and pin define
Reason: Fool-proof is not good (ME)
Possible Risk:

P44_ Delete U5102~U5105
Reason: Manufacturing request can not co-lay
Possible Risk:

P50_ R6803, R6810 change to 220 ohm
Reason: Adjust LED brightness
Possible Risk: Rework OK

P51_ Delete D6501, R6517, R6516; Add Q6505, Q6506, R6504,R6503
Reason: Manufacturing request can direct use debug card
Possible Risk: Rework OK

P58_ Mount D46 schottky diode(Q00033)
Reason: Customer request
Possible Risk: Rework OK

P68_ R9303 change to 4.7K, R9315 change to 7.5K
C9309 cgange to 0.47uF
Reason: For VEVs report GPU sequence timing
Possible Risk: Rework OK

(2011/01/17~01/25)

P32_ Change BAT1 connector to 20.81602.007
Reason: Solve hitting L-case or battery shutdown issue (ME)
Possible Risk:

P58_ D46 change to Schottky diode 83.R2004.B8F(Q00033)
Reason: Customer request
Possible Risk: Rework OK

P33_ 58_Delete Q57, Add PR4021~PR4023, PQ4008, PQ4009, PQ4011
Reason: Provide DCBATOUT short surge current (power team)
Possible Risk: Rework OK

P9_C901, C903, C904, C905 and C906 change to 22uF
Reason: For GFX power ripple
Possible Risk: Rework OK

P23_R2707 change to 47K
Reason: For UMA 75W setting
Possible Risk:

P23_R2724 change to 47K
Reason: For -1 version
Possible Risk:

P17_R2127~R2130 change to 47 ohm,R2130 change to 0 ohm
C2105, C2107, C2108, C2109 change to 22pF
Reason: For VEVs LPC report
Possible Risk:

P15_ D1901 change to dual schottky , dummy Q1904,
R1911 change to 1K, R1910 change to 10K ,add R1924(Q00003)
Reason: Customer request
Possible Risk: Rework OK

P29_R3619 change to 0 ohm, add R3622=10K
R3623, R3624, R3627, R3628=0 ohm, Dummy C3614
Reason: Customer request
Possible Risk: Rework OK

P25,P28_ 46_Dummy R2922 ,Q17~Q22, R329 R331 , R330, R333,C404, R5801~R5804, C5801, C5804, C5805, C5806, U5801, U5802(Q00042)
Reason: Customer request for External De-pop Circuit Eliminating Trial (Q00043)
Possible Risk: Rework OK

P22_ Q2602 change to FET MOS
Reason: Customer request
Possible Risk: Rework OK

P33_ PR4404 change to 715
Reason: For VCC_GFXCORE OCP protect (power team)
Possible Risk:

P36_ PT4301,PT4303,PT4304,PT4305,PT4309, Dummy PT4308
Reason: For CPU transient (power team)
Possible Risk:

P35_ PR4227 change to 3.57K
Reason: For CPU load line (power team)
Possible Risk:

P35_ PR4218 change to 33.2K
Reason: For CPU lmon setting (power team)
Possible Risk:

P37_PR4404 change to 715 ohm
Reason: For 3/5V OCP protect (power team)
Possible Risk: Rework OK

P35_PR4205 change to 2.74K
Reason: For CPU load line (power team)
Possible Risk: Rework OK

P35_PR4206 change to 17.8K
Reason: For CPU lmon setting (power team)
Possible Risk: Rework OK

P45_Dummy C5604 ,R5603 change to 0 ohm,add R5604_7.5 ohm ,change Q5601(Q00011)
Reason: Customer request
Possible Risk: Rework OK

(2011/01/17~01/26)

P22_ R2635 change to 11K
Reason: Customer request
Possible Risk: Rework OK

P39_ PR4603 change to 16.2K
Reason: For 1.5V OCP protect (power team)
Possible Risk: Rework OK

P38_ PR4504 change to 93.1K
Reason: For 1.05V OCP protect (power team)
Possible Risk: Rework OK

P42_ Add EC4901
Reason:LDC connector DCBATOUT (EMI team)
Possible Risk: Rework OK

P58_ Add R496,R505,R499,C569,R495,R500,R518,R511
Reason:UVP protect(Customer request)
Possible Risk:

(2011/01/27)

P15_DUMMY R1925(SUSPWRDNACK)
Reason:intel HR schematic check list
Possible Risk:Rework OK

P15_ Q1904 change to 84.03k15.A31
Reason:Low VGS
Possible Risk:Rework OK

P58_Del R496,R505,R499,C569,R495,R500,R518,R511
Dummy:C568, C9322 and D46
Reason:UVP protect(Customer request)
Possible Risk:

P33_ add PC4025,PC4024,PR4207,PR4220,PQ4010,PR4552,PR4026,PQ4015
Reason:UVP protect(Customer request)
Possible Risk:

(2011/01/31)

P38_ Dummy PR4509,PR4506
Reason:For 1.05v VCCIO_SENSE ,dummy 1.05v is better
Possible Risk:Rework OK

(2011/02/08)

P41_ Add PR4808, PR4809, PR4810(DUMMY)
Reason: for intel released
new spec of Celeron and Pentium CPU VCCSA_PWR
Possible Risk:

(2011/02/09)

Add Aluminum Solid Capacitors 2ND source
Reason: Material shortage issue
Possible Risk:

P58_ Add D46
Reason:
Possible Risk:

(2011/02/11)

P25_ Change RN2901 to 22 ohm
Reason: DMIC VEVs report
Possible Risk:

(2011/02/14)

P69_DUMMY SPR1
Reason: factory damage issue
Possible Risk:

P40_change PU4701 new version
Reason: old will EOL
Possible Risk:

P58_ ADD D46,R498 change to 1M ohm
Reason:UVP protect
Possible Risk:Rework ok

P33_ DUMMY PR4026,PQ4015,PR4252,PR4022,PQ4011
Reason:UVP protect
Possible Risk:Rework ok

P25_ Delete EC2901 and EC2902
Reason: For D-MIC record sound quietly
Possible Risk: Rework OK

Reversion History

-1M

(2011/03/02)

P23_R2724 change to 64.9K
Reason: For -1M version
Possible Risk:

MATSUKI capacitance 47U/ 25V change to NCC
Reason:MATSUKI test failure issue
Possible Risk:

N12M GS2 HYN1GB

緯創資通

Wistron Corporation

21F, 88, Sec.1, Hsin Tai Wu Rd., Hsichih, Taipei Hsien 221, Taiwan, R.O.C.

File

Change History

Size

Document Number

Rev

Date

Thursday, March 03, 2011

Sheet 74 of 74

Z50-HR (Huron River Platform)

-1